



44 FARRAND STREET  
BLOOMFIELD, NJ 07003  
(973) 748-5089

## **NTE990** **Integrated Circuit** **Dual Audio Power Amplifier**

### **Description:**

The NTE990 is a monolithic dual power amplifier designed to deliver 2W/channel continuous into  $8\Omega$  loads. The NTE990 is designed to operate with a low number of external components, and still provide flexibility for use in stereo phonographs, tape records and AM-FM stereo receivers, etc. Each power amplifier is biased from a common internal regulator to provide high power supply rejection, and output Q point centering. The NTE990 is internally compensated for all gains greater than 10.

### **Features:**

- 2W/channel
- -65 dB Ripple Rejection, Output Referred
- -65 dB Channel Separation, Output Referred
- Wide Supply Range: 6V to 24V
- Very Low Cross-Over Distortion
- Low Audio Band Noise
- AC Short Circuit Protected
- Internal Thermal Shutdown

### **Applications:**

- Multi-Channel Audio Systems
- Stereo Phonographs
- Tape Recorders and Players
- AM-FM Radio Receivers
- Servo Amplifiers
- Intercom Systems
- Automotive Products

### **Absolute Maximum Ratings:**

Supply Voltage, $V_{CC}$ .....	26V
Input Voltage, $V_I$ .....	$\pm 0.7V$
Operating Junction Temperature, $T_J$ .....	+150°C
Operating Temperature Range, $T_{opr}$ .....	0° to +70°C
Storage Temperature Range, $T_{stg}$ .....	-65° to +150°C
Lead Temperature (During Soldering, 10sec), $T_L$ .....	+300°C

**Electrical Characteristics:** ( $V_S = 20V$ ,  $T_A = +25^\circ C$ ,  $R_L = 8\Omega$ ,  $A_V = 50$  (34 dB) unless otherwise specified)

Parameter	Test Conditions		Min	Typ	Max	Unit
Total Supply Current	$P_O = 0W$		—	25	50	mA
Output Power	THD = 10%		2.0	—	—	W/Ch
Total Harmonic Distortion	$f = 1kHz$ , $V_S = 14V$	$P_O = 50mW/Ch$	—	0.075	—	%
		$P_O = 500mW/Ch$	—	0.045	—	%
		$P_O = 1W/Ch$	—	0.055	—	%
Output Swing	$R_L = 8\Omega$		—	$V_S - 6$	—	$V_{P-P}$
Channel Separation	$C_F = 50\mu F$ , $C_{IN} = 0.1\mu F$ , $f = 1kHz$ , Output Referred	$V_S = 20V$ , $V_O = 4V_{rms}$	-50	-70	—	dB
		$V_S = 7V$ , $V_O = 0.5V_{rms}$	—	-60	—	dB
Power Supply Rejection Ratio	$C_F = 50\mu F$ , $C_{IN} = 0.1\mu F$ , $f = 120Hz$ , Output Referred	$V_S = 20V$ , $V_{ripple} = 1V_{rms}$	-50	-65	—	dB
		$V_S = 7V$ , $V_{ripple} = 0.5V_{rms}$	—	-40	—	dB
Equivalent Noise Input	$R_S = 0$ , $C_{IN} = 0.1\mu F$ , BW = 20Hz to 20kHz, Output Noise Wideband		—	2.5	—	$\mu A$
	$R_S = 0$ , $C_{IN} = 0.1\mu F$ , $A_V = 200$		—	0.8	—	mV
Open Loop Gain	$R_S = 0$ , $f = 100kHz$ , $R_L = 8\Omega$		—	70	—	dB
Input Offset Voltage			—	15	—	mV
Input Bias Current			—	50	—	nA
Input Impedance	Open Loop		—	4	—	$M\Omega$
DC Output Level	$V_S = 20V$		9	10	11	V
Slew Rate			—	2.0	—	$V/\mu s$
Power Bandwidth			—	65	—	kHz
Current Limit			—	1.0	—	A

Note 1 For operation at ambient temperature greater than  $+25^\circ C$ , the NTE990 must be derated based on a maximum  $150^\circ C$  junction temperature using a thermal resistance which depends upon device mounting techniques..

Pin Connection Diagram



