



Intellimod™-3 Modules
Single Phase
IGBT Inverter Output
200 Amperes/460 Volt Line



Description

Powerex Intellimod-3 Modules are designed for applications requiring a high frequency (20kHz) output switching inverter. The modules are isolated from the baseplate, consisting of complete drive, control and protection circuitry for the IGBT inverter.

Features:

- Complete Output Power Circuit
- Gate Drive Circuit
- Protection Logic
 - Short Circuit
 - Over-Current
 - Over Temperature
 - Under Voltage

Applications:

- Inverters
- Small UPS
- Motion/Servo Control
- AC Motor Control

Ordering Information

PM200DHA120

460 Volt Line, PM200DHA120 Outline Drawing

Dimensions	Inches	Millimeters
A	5.12	130.0
B	4.33±0.10	110.0±0.25
C	3.54	90.0
D	2.76±0.10	70.0±0.25
E	1.61	41.0
F	1.34+0.04/-0.02	34.0+1.0/-0.5
G	1.22	31.0
H	1.1	28.0
J	1.06	27.0

Dimensions	Inches	Millimeters
K	0.71	18.0
L	0.57	14.5
M	0.53	13.5
N	0.51	13.0
P	Metric M8	M8
Q	0.28	7.0
R	0.26 Dia.	6.5 Dia.
S	0.1	2.54
T	0.8 Dia.	2.0 Dia.

POWEREX INC

51E D ■ 7294621 0005785 T7T ■ PRX

Powerex, Inc., Hillis Street, Youngwood, Pennsylvania 15697 (412) 925-7272
Powerex, Europe, S.A. 428 Avenue G. Durand, BP107, 72003 Le Mans, France (43) 41.14.14
PM200DHA120
Intellimod-3 Modules
Single Phase IGBT Inverter Output
200 Amperes/460 Volt Line

T-57-29

Absolute Maximum Ratings, $T_j = 25^\circ\text{C}$ unless otherwise specified

Characteristics	Symbol	PM200DHA120	Units
Power Device Junction Temperature	T_j	-20 to +150	°C
Storage Temperature	T_{STG}	-40 to +125	°C
Case Operating Temperature	T_c	-20 to +100	°C
Mounting Torque, M6 Mounting Screws	—	30	Kg-cm
Mounting Torque, M8 Main Terminal Screws	—	110	Kg-cm
Module Weight (Typical)	—	910	Grams
Supply Voltage Protected by OC and SC ($V_D = 13.5 - 16.5\text{V}$, Inverter Part)	$V_{CC(\text{prot})}$	800	Volts
Isolation Voltage AC 1 minute, 60Hz	V_{RMS}	2500	Volts

Control Sector

Supply Voltage Applied between ($V_{P1} - V_{PC}$, $V_{N1} - V_{NC}$)	V_D	20	Volts
Input Voltage Applied between ($C_{P1} - V_{PC}$, $C_{N1} - V_{NC}$)	V_{CIN}	10	Volts
Fault Output Supply Voltage Applied between ($F_{PO} - V_{PC}$, $F_{NO} - V_{NC}$)	V_{FO}	20	Volts
Fault Output Current (Sink Current at F_{PO} , F_{NO} Terminals)	I_{FO}	20	mA

IGBT Inverter Sector

Collector-Emitter Voltage	V_{CES}	1200	Volts
Collector Current \pm	I_C	200	Amperes
Peak Collector Current \pm	I_{CP}	400	Amperes
Supply Voltage (Applied between P - N)	V_{CC}	900	Volts
Supply Voltage (Surge) Applied between P - N	$V_{CC(\text{surge})}$	1000	Volts
Collector Dissipation	P_C	1470	Watts

Powerex, Inc., Hillis Street, Youngwood, Pennsylvania 15697 (412) 925-7272

Powerex, Europe, S.A. 428 Avenue G. Durand, BP107, 72003 Le Mans, France (43) 41.14.14

T-57-29

PM200DHA120
Intellimod-3 Modules
Single Phase IGBT Inverter Output

200 Amperes/460 Volt Line

Electrical Characteristics, $T_j = 25^\circ\text{C}$ unless otherwise specified

Characteristics	Symbol	Test Conditions	Min.	Typ.	Max.	Units
Control Sector						
Overcurrent Trip Level	OC	-20°C ≤ T ≤ 125°C, Fig. 5	240	360	—	Amperes
Short Circuit Trip Level	SC	-20°C ≤ T ≤ 125°C, Fig. 5	320	540	—	Amperes
Over Current Delay Time	$t_{off(OC)}$	$V_D = 15V$, Fig. 5	—	5	—	μS
Over Temperature Protection	OT	Trip Level	100	110	120	°C
Over Temperature Protection	OT _R	Reset Level	85	95	105	°C
Supply Circuit Under Voltage Protection	UV	Trip Level	11.5	12.0	12.5	Volts
Supply Circuit Under Voltage Protection	UV _R	Reset Level	—	12.5	—	Volts
Supply Voltage	V_D	Applied between $V_{P1} - V_{PC}, V_{N1} - V_{NC}$	13.5	15	16.5	Volts
Circuit Current	I_D	$V_D = 15V, V_{CIN} = 5V, V_{N1} - V_{NC}$	—	23	30	mA
	I_D	$V_D = 15V, V_{CIN} = 5V, V_{P1} - V_{PC}$	—	23	30	mA
Input On Voltage	$V_{CIN(on)}$	Applied between	1.2	1.5	1.8	Volts
Input Off Voltage	$V_{CIN(off)}$	$C_{P1} - V_{PC}, C_{N1} - V_{NC}$	1.7	2.0	2.3	Volts
PWM Input Frequency	f_{PWM}	3-Ø Sinusoidal	—	15	20	kHz
Dead Time	t_{DEAD}	For each Input Pulse	4.0	—	—	μS
		Using example Interface Circuit*	6.0	—	—	μS
Fault Output Current	$I_{FO(H)}$	$V_D = 15V, V_{FO} = 15V$	—	—	0.01	mA
	$I_{FO(L)}$	$V_D = 15V, V_{FO} = 15V$	—	10	15	mA
Minimum Fault Output Pulse Width	t_{FO}	$V_D = 15V$	1.0	1.8	—	ms
SXR Terminal Output Voltage	V_{SXR}	$T_j = 125^\circ\text{C}, R_{IN} = 6.8\text{k}\Omega, (S_{PR}, S_{NR})$	4.5	5.1	5.6	Volts

*See Intellimod-3 Applications Data Section 4.3.

Powerex, Inc., Hillis Street, Youngwood, Pennsylvania 15697 (412) 925-7272

Powerex, Europe, S.A. 428 Avenue G. Durand, BP107, 72003 Le Mans, France (43) 41.14.14

T-57-29

PM200DHA120**Intellimod-3 Modules****Single Phase IGBT Inverter Output**

200 Amperes/460 Volt Line

Electrical Characteristics, $T_j = 25^\circ\text{C}$ unless otherwise specified

Characteristics	Symbol	Test Conditions	Min.	Typ.	Max.	Units
IGBT Inverter Sector						
Collector Cutoff Current	I_{CEX}	$V_{CE} = V_{CES}$, $T_j = 25^\circ\text{C}$, Fig. 4	—	—	1	mA
Collector Cutoff Current	I_{CEX}	$V_{CE} = V_{CES}$, $T_j = 125^\circ\text{C}$, Fig. 4	—	—	10.0	mA
Diode Forward Voltage	V_{FM}	$-I_C = 200\text{A}$, $V_{CIN} = 5\text{V}$, Fig. 2	—	1.8	3.0	Volts
Collector Emitter Saturation Voltage	$V_{CE(\text{sat})}$	$V_D = 15\text{V}$, $V_{CIN} = 0\text{V}$, $I_C = 200\text{A}$, Fig. 1	—	2.8	3.8	Volts
Collector Emitter Saturation Voltage	$V_{CE(\text{sat})}$	$V_D = 15\text{V}$, $V_{CIN} = 0\text{V}$, $I_C = 200\text{A}$, $T_j = 125^\circ\text{C}$, Fig. 1	—	2.4	3.4	Volts
Inductive Load Switching Times						
	t_{on}	$V_D = 15\text{V}$, $V_{CIN} = 0\text{V}$,	0.5	1.4	2.5	μs
	t_{rr}	$V_{CC} = 600\text{V}$, $I_C = 200\text{A}$,	—	0.3	0.6	μs
	$t_{C(on)}$	$T_j = 125^\circ\text{C}$	—	0.4	1.0	μs
	t_{off}		—	3.5	4.0	μs
	$t_{C(off)}$	Fig. 3	—	0.8	1.2	μs

Thermal Characteristics

Characteristics	Symbol	Test Conditions	Min.	Typ.	Max.	Units
Thermal Resistances Junction to Case	$R_{th(j-c)Q}$	Inverter IGBT	—	—	0.085	$^\circ\text{C}/\text{W}$
	$R_{th(j-c)F}$	Inverter FWD	—	—	0.18	$^\circ\text{C}/\text{W}$
Contact Thermal Resistance	$R_{th(c-f)}$	Case to Fin, Thermal Grease Applied	—	—	0.060	$^\circ\text{C}/\text{W}$

Recommended Operating Conditions

Characteristics	Symbol	Test Conditions	Value	Units
Supply Voltage	V_{CC}	Applied across C1 - E2 Terminals	0 ~ 800	Volts
	V_D	Applied between $V_{P1} - V_{PC}$, $V_{N1} - V_{NC}$	15 ± 1.5	Volts
Input On Voltage	$V_{CIN(on)}$	Applied between $C_{P1} - V_{PC}$, $C_{N1} - V_{NC}$	0 ~ 0.8	Volts
Input Off Voltage	$V_{CIN(off)}$		$4 \sim V_{SXR}$	Volts
PWM Input Frequency	f_{PWM}	Using example Interface Circuit*	5 ~ 20	kHz
Minimum Dead Time	t_{DEAD}	Using example Interface Circuit*	6.0	μs

*See Intellimod-3 Applications Data Section 4.3.

Powerex, Inc., Hillis Street, Youngwood, Pennsylvania 15697 (412) 925-7272

Powerex, Europe, S.A. 428 Avenue G. Durand, BP107, 72003 Le Mans, France (43) 41.14.14

T-57-2


PM200DHA120

Intellimod-3 Modules

Single Phase IGBT Inverter Output

200 Amperes/460 Volt Line

A) LOWER ARM SWITCHING



B) UPPER ARM SWITCHING





Figure 3 Switching Test

Powerex, Inc., Hillis Street, Youngwood, Pennsylvania 15697 (412) 925-7272

Powerex, Europe, S.A. 428 Avenue G. Durand, BP107, 72003 Le Mans, France (43) 41.14.14

PM200DHA120

Intellimod-3 Modules

Single Phase IGBT Inverter Output

200 Amperes/460 Volt Line




Figure 4 I_{CES} Test




Figure 5 Over Current and
Short Circuit Test