

Preliminary

SPCA504A
Data Sheet

Dual Mode PC Camera Processor

Scatch
Sunplus Camera Solution

SPCA504A

Data Sheet

Version 0.2.1

SUNPLUS TECHNOLOGY CO. reserves the right to change this documentation without prior notice. Information provided by SUNPLUS TECHNOLOGY CO. is believed to be accurate and reliable. However, SUNPLUS TECHNOLOGY CO. makes no warranty for any errors which may appear in this document. Contact SUNPLUS TECHNOLOGY CO. to obtain the latest version of device specifications before placing your order. No responsibility is assumed by SUNPLUS TECHNOLOGY CO. for any infringement of patent or other rights of third parties which may result from its use. In addition, SUNPLUS products are not authorized for use as critical components in life support devices/ systems or aviation devices/systems, where a malfunction or failure of the product may reasonably be expected to result in significant injury to the user, without the express written approval of Sunplus.

Table of Contents

1. GENERAL DESCRIPTION	3
2. FEATURE	3
3. PIN DESCRIPTION	4
3.1 PIN ASSIGNMENT FOR 160-PIN PACKAGE	4
3.2 PIN ASSIGNMENT FOR 128-PIN PACKAGE	10
4. FUNCTIONAL DESCRIPTION	15
4.1 BLOCK DIAGRAM	15
4.2. CAMERA OPERATION MODES	16
5. PACKAGE - 160 PINS	17
6. PACKAGE - 128 PINS	19
REVISION HISTORY	20

1. General description

The SPCA504A is a digital camera processor chip that provides a complete solution for dual mode camera applications. This chip integrates image sensor interface, digital video input interface, color image processor, storage media controller, JPEG image compression engine, USB interface, and a built-in micro-controller. The SPCA504A supports both CCD and CMOS image sensors up to 1.1M and 2.0M pixels respectively. It is designed to fulfill all the requirements for the dual mode camera applications. The SPCA504A camera processor chip includes not only the latest technology, but also the full services and support of Sunplus.

2. Feature

The main functions of the SPCA504A includes:

- DSC mode : capture one frame each time
- Video clip mode : capture a video with frame rate 15~30 frames/sec
- PC-camera mode : 30 frames/sec for CIF size, 20 frames/sec for VGA size

The SPCA504A chip has many image-processing functions that include:

- High quality color interpolation
- Two-dimensional edge enhancement
- Bad pixels concealment
- AE/AWB parameter windows cover full range of the sensor

The SPCA504A supports image CCD/CMOS sensors up to 1.1M/2.1M pixels. Some of them are listed below.

CCD

- VGA : Sharp LZ24BP, Sony ICX098AK, Panasonic MN3777
- XGA : Sony ICX204AK
- SXGA : Panasonic MN3778 (progressive)

CMOS

- VGA: HP HDCS2020, PHOTOBIT PB320, OMMNIVISION OV7620, HYUNDAI HV7131B, SHARP LZ34B10, PIXART PAS202, TASC TAS5130A, BIOMORPHIC BI8602, IC MEDIA ICM205DL, MOTOROLA SCM20014, National Semiconductor LM9627, Century Semiconductor CS2102
- SVGA: HYUNDAI HV7141B
- XGA : PIXELCAM PCS2112
- SXGA: Motorola MCM20027

The DRAM interface supports 16M bits and 64M bits SDRAM modules through a 16-bit data bus.

Audio functions that the SPCA504A supports include audio class, audio capture, audio record and playback.

- It supports bi-directional AC-link for audio record and playback.
- It supports MP3 decoder interface for MP3 decoding and playback.
- It supports microphone interface for audio record.
- It supports an IMA-ADPCM compatible ADPCM compression engine for audio compression.

In addition to the external SDRAM module, the SPCA504A supports many storage media. That include:

- NAND-gate flash memory (smart media card)
- NOR-type flash memory
- ATAPI interface (ATAPI CDRW, compact flash memory)
- SPI serial flash memory, both mode0 and mode 3 supported (MultiMediaCard)
- Next Flash serial flash memory
- SD Card

The SPCA504A supports JPEG image compression at YUV422 and YUV 420 chroma format. It can also compress BW (black-and-white) images. The output data format is compliant with JFIF bitstream format. An automatic scale-down function is included to fit in the display size under playback mode.

The USB interface supports following pipes to PC. They are:

- Video ISO-IN pipe : for video data transmission to the PC
- Audio ISO-IN pipe : for Audio data transmission to the PC
- BULK-IN pipe : for uploading image from the camera to the PC
- BULK-OUT pipe : for download image data, audio data, firmware, and MP3 data to the camera.
- INTERRUPT-IN pipe: For reporting status and events of the camera to the PC

The SPCA504A has a built-in 8032 micro-controller with 6K bytes of internal SRAM.

- It supports *ISP* (in-system-programming with 4K bytes of shadow space).
- It has built-in 64K bytes of mask ROM.
- It supports *LOW-POWER* mode and *IDLE* mode.

The SPCA504A has a built-in PLL to supply on-chip clock sources.

The SPCA504A is packaged in either 128-pin QFP or 160-pin LQFP.

The SPCA504A needs 3.3/2.5 dual power supply.

3. Pin description

3.1 Pin assignment for 160-pin package

Pin	Signal	Pin	Signal
1	rgb5	80	fmgpio2
2	rgb6	81	fmgpio3
3	rgb7	82	fmgpio4
4	rgb8	83	fmgpio5 / ma12
5	rgb9	84	fmgpio6 / ma13
6	v1	85	fmgpio7
7	v2	86	fmgpio8
8	v3	87	fmgpio9
9	sg	88	fmgpio10
10	sub	89	fmgpio11
11	fr	90	fmgpio12
12	fh1	91	dvss2
13	fh2	92	dvdd2
14	pb1k	93	md15
15	ovdd4	94	md14
16	ovss4	95	md13
17	rs	96	md12
18	fs	97	md11
19	fedc	98	md10
20	adclp	99	md9
21	obclp	100	md8
22	adek	101	md7
23	sen	102	md6
24	sck	103	md5
25	sdo	104	md4
26	dvdd4	105	md3
27	dvss4	106	md2
28	avss4	107	md1
29	avss	108	md0
30	alc	109	ovss2
31	mic	110	ovdd2
32	opi	111	p35
33	opo	112	p34
34	avdd	113	p31
35	vref	114	p30
36	uvss	115	p17
37	dp	116	p16
38	dm	117	p15
39	uvdd	118	p14
40	suspend	119	p13
41		120	
42		121	
43		122	
44		123	
45		124	
46		125	
47		126	
48		127	
49		128	
50		129	
51		130	
52		131	
53		132	
54		133	
55		134	
56		135	
57		136	
58		137	
59		138	
60		139	
61		140	
62		141	
63		142	
64		143	
65		144	
66		145	
67		146	
68		147	
69		148	
70		149	
71		150	
72		151	
73		152	
74		153	
75		154	
76		155	
77		156	
78		157	
79		158	
80		159	
81		160	

SPCA504A
(160 pin)