



PNP Silicon Digital Transistor

- Switching circuit, inverter, interface circuit, driver circuit.
- Built in bias resistor ($R_1 = 10k\Omega$)
- For 6-PIN packages: two (galvanic) internal isolated transistors with good matching in one package



**BCR179F/L3
BCR179T**

SEMB4



Type	Marking	Pin Configuration						Package
		1=B	2=E	3=C	-	-	-	
BCR179F	WWs	1=B	2=E	3=C	-	-	-	TSFP-3
BCR179L3	WW	1=B	2=E	3=C	-	-	-	TSLP-3-4
BCR179T	WWs	1=B	2=E	3=C	-	-	-	SC75
SEMB4	WW	1=E1	2=B1	3=C2	4=E2	5=B2	6=C1	SOT666

Maximum Ratings

Parameter	Symbol	Value	Unit
Collector-emitter voltage	V_{CEO}	50	V
Collector-base voltage	V_{CBO}	50	
Emitter-base voltage	V_{EBO}	5	
Input on voltage	$V_{i(on)}$	20	
Collector current	I_C	100	mA
Total power dissipation	P_{tot}		mW
BCR179F, $T_S \leq 128^\circ\text{C}$		250	
BCR179L3, $T_S \leq 135^\circ\text{C}$		250	
BCR179T, $T_S \leq 109^\circ\text{C}$		250	
SEMB4, $T_S \leq 75^\circ\text{C}$		250	
Junction temperature	T_j	150	°C
Storage temperature	T_{stg}	150 ... -65	

Thermal Resistance

Parameter	Symbol	Value	Unit
Junction - soldering point ¹⁾	R_{thJS}		K/W
BCR179F		≤ 90	
BCR179L3		≤ 60	
BCR179T		≤ 109	
SEMB4		≤ 300	

¹⁾For calculation of R_{thJA} please refer to Application Note Thermal Resistance


Electrical Characteristics at $T_A = 25^\circ\text{C}$, unless otherwise specified

Parameter	Symbol	Values			Unit
		min.	typ.	max.	
DC Characteristics					
Collector-emitter breakdown voltage $I_C = 100 \mu\text{A}, I_B = 0$	$V_{(BR)CEO}$	50	-	-	V
Collector-base breakdown voltage $I_C = 10 \mu\text{A}, I_E = 0$	$V_{(BR)CBO}$	50	-	-	
Emitter-base breakdown voltage $I_E = 10 \mu\text{A}, I_C = 0$	$V_{(BR)EBO}$	5	-	-	
Collector-base cutoff current $V_{CB} = 40 \text{ V}, I_E = 0$	I_{CBO}	-	-	100	nA
DC current gain ¹⁾ $I_C = 5 \text{ mA}, V_{CE} = 5 \text{ V}$	h_{FE}	120	-	630	-
Collector-emitter saturation voltage ¹⁾ $I_C = 10 \text{ mA}, I_B = 0,5 \text{ mA}$	V_{CEsat}	-	-	0,3	V
Input off voltage $I_C = 100 \mu\text{A}, V_{CE} = 5 \text{ V}$	$V_{i(off)}$	0,4	-	1	
Input on voltage $I_C = 2 \text{ mA}, V_{CE} = 0,3 \text{ V}$	$V_{i(on)}$	0,5	-	1,1	
Input resistor	R_1	7	10	13	k Ω
AC Characteristics					
Transition frequency $I_C = 10 \text{ mA}, V_{CE} = 5 \text{ V}, f = 100 \text{ MHz}$	f_T	-	150	-	MHz
Collector-base capacitance $V_{CB} = 10 \text{ V}, f = 1 \text{ MHz}$	C_{cb}	-	1,2	-	pF

¹⁾Pulse test: $t < 300 \mu\text{s}; D < 2\%$


DC current gain $h_{FE} = f(I_C)$

$V_{CE} = 5\text{ V}$ (common emitter configuration)




Collector-emitter saturation voltage

$V_{CEsat} = f(I_C), h_{FE} = 20$




Input on Voltage $V_{i(on)} = f(I_C)$

$V_{CE} = 0.3\text{ V}$ (common emitter configuration)




Input off voltage $V_{i(off)} = f(I_C)$

$V_{CE} = 5\text{ V}$ (common emitter configuration)




Total power dissipation $P_{tot} = f(T_S)$

BCR179F




Total power dissipation $P_{tot} = f(T_S)$

BCR179L3




Total power dissipation $P_{tot} = f(T_S)$

BCR179T




Total power dissipation $P_{tot} = f(T_S)$

SEMB4



Permissible Puls Load $R_{thJS} = f(t_p)$


BCR179F



Permissible Pulse Load


$P_{totmax}/P_{totDC} = f(t_p)$

BCR179F



Permissible Puls Load $R_{thJS} = f(t_p)$


BCR179L3



Permissible Pulse Load


$P_{totmax}/P_{totDC} = f(t_p)$

BCR179L3



Permissible Puls Load $R_{thJS} = f(t_p)$


BCR179T



Permissible Pulse Load


$P_{totmax}/P_{totDC} = f(t_p)$

BCR179T



Permissible Puls Load $R_{thJS} = f(t_p)$


SEMB4



Permissible Pulse Load

$P_{totmax}/P_{totDC} = f(t_p)$

SEMB4



**Published by Infineon Technologies AG,
St.-Martin-Strasse 53,
81669 München**

**© Infineon Technologies AG 2004.
All Rights Reserved.**

Attention please!

The information herein is given to describe certain components and shall not be considered as a guarantee of characteristics.

Terms of delivery and rights to technical change reserved.

We hereby disclaim any and all warranties, including but not limited to warranties of non-infringement, regarding circuits, descriptions and charts stated herein.

Information

For further information on technology, delivery terms and conditions and prices please contact your nearest Infineon Technologies Office (www.infineon.com).

Warnings

Due to technical requirements components may contain dangerous substances. For information on the types in question please contact your nearest Infineon Technologies Office.

Infineon Technologies Components may only be used in life-support devices or systems with the express written approval of Infineon Technologies, if a failure of such components can reasonably be expected to cause the failure of that life-support device or system, or to affect the safety or effectiveness of that device or system. Life support devices or systems are intended to be implanted in the human body, or to support and/or maintain and sustain and/or protect human life. If they fail, it is reasonable to assume that the health of the user or other persons may be endangered.