

# NESG340034

R09DS0023EJ0200

## NPN Silicon Germanium RF Transistor

Rev.2.00

Aug 18, 2011

### DESCRIPTION

The NESG340034 is an ideal choice for low noise, low distortion amplification.

### FEATURES


- NF = 0.65 dB TYP. @  $V_{CE} = 5\text{ V}$ ,  $I_C = 15\text{ mA}$ ,  $f = 1\text{ GHz}$
- $P_{o(1\text{ dB})} = 24\text{ dBm}$  TYP. @  $V_{CE} = 5\text{ V}$ ,  $I_{C(\text{set})} = 40\text{ mA}$ ,  $f = 1\text{ GHz}$
- $OIP_3 = 35.5\text{ dBm}$  TYP. @  $V_{CE} = 5\text{ V}$ ,  $I_{C(\text{set})} = 40\text{ mA}$ ,  $f = 1\text{ GHz}$
- Maximum stable power gain: MSG = 12.0 dB TYP. @  $V_{CE} = 5\text{ V}$ ,  $I_C = 40\text{ mA}$ ,  $f = 1\text{ GHz}$
- SiGe HBT technology (UHS3) :  $f_T = 10\text{ GHz}$
- This product is improvement of ESD
- 3-pin power minimold (34 PKG)

### APPLICATIONS

- Suitable for up to 1 GHz applications.  
e.g. LNA (Low Noise Amplifier) or booster amplifier for Digital-TV.

### OUTLINE

RENESAS Package code: 34  
(Package name: 3-pin power minimold (34 PKG))



1. Emitter
2. Collector
3. Base

Note: Marking is "ST"

### ORDERING INFORMATION

Part Number	Order Number	Package	Quantity	Supplying Form
NESG340034	NESG340034-A	3-pin power minimold (34 PKG) (Pb-Free)	25 pcs (Non reel)	<ul style="list-style-type: none"> <li>• Magazine case</li> </ul>
NESG340034-T1	NESG340034-T1-A		1 kpcs/reel	<ul style="list-style-type: none"> <li>• Embossed tape 12 mm wide</li> <li>• Pin 2 face the perforation side of the tape</li> </ul>

**Remark** To order evaluation samples, please contact your nearby sales office.  
Unit sample quantity is 25 pcs.

### CAUTION

Observe precautions when handling because these devices are sensitive to electrostatic discharge.

The mark <R> shows major revised points.

The revised points can be easily searched by copying an "<R>" in the PDF file and specifying it in the "Find what:" field.

**ABSOLUTE MAXIMUM RATINGS (T<sub>A</sub> = +25°C)**

Parameter	Symbol	Ratings	Unit
Collector to Base Voltage	V <sub>CBO</sub>	5.5	V
Collector to Emitter Voltage (Base Short)	V <sub>CES</sub>	13	V
Collector to Emitter Voltage (Base Open)	V <sub>CEO</sub>	5.5	V
Base Current <sup>Note1</sup>	I <sub>B</sub>	36	mA
Collector Current	I <sub>C</sub>	400	mA
Total Power Dissipation <sup>Note2</sup>	P <sub>tot</sub>	886	mW
Junction Temperature	T <sub>j</sub>	150	°C
Storage Temperature	T <sub>stg</sub>	-65 to +150	°C

Notes: 1. Depend on the ESD protect device.

2. Mounted on 3.8 cm × 9.0 cm × 0.8 mm (t) glass epoxy PWB

**THERMAL RESISTANCE (T<sub>A</sub> = +25°C)**

Parameter	Symbol	Ratings	Unit
Thermal Resistance from Junction to Ambient <sup>Note</sup>	R <sub>thj-a</sub>	141	°C/W

Note: Mounted on 3.8 cm × 9.0 cm × 0.8 mm (t) glass epoxy PWB

**RECOMMENDED OPERATING RANGE (T<sub>A</sub> = +25°C)**

Parameter	Symbol	MIN.	TYP.	MAX.	Unit
Collector Current	I <sub>C</sub>	–	40	–	mA

**ELECTRICAL CHARACTERISTICS (T<sub>A</sub> = +25°C)**

&lt;R&gt;

Parameter	Symbol	Test Conditions	MIN.	TYP.	MAX.	Unit
DC Characteristics						
Collector Cut-off Current	I <sub>CBO</sub>	V <sub>CB</sub> = 5 V, I <sub>E</sub> = 0	–	–	100	nA
Emitter Cut-off Current	I <sub>EBO</sub>	V <sub>EB</sub> = 0.4 V, I <sub>C</sub> = 0	–	–	100	nA
DC Current Gain	h <sub>FE</sub> <sup>Note 1</sup>	V <sub>CE</sub> = 5 V, I <sub>C</sub> = 15 mA	200	320	500	–
RF Characteristics						
Gain Bandwidth Product	f <sub>T</sub>	V <sub>CE</sub> = 5 V, I <sub>C</sub> = 40 mA, f = 1 GHz	–	10.0	–	GHz
Insertion Power Gain	S <sub>21e</sub>   <sup>2</sup>	V <sub>CE</sub> = 5 V, I <sub>C</sub> = 40 mA, f = 1 GHz	8.5	10.5	–	dB
Noise Figure (1)	NF1	V <sub>CE</sub> = 5 V, I <sub>C</sub> = 15 mA, f = 1 GHz, Z <sub>S</sub> = Z <sub>Sopt</sub> , Z <sub>L</sub> = 50 Ω	–	0.65	1.05	dB
Noise Figure (2)	NF2	V <sub>CE</sub> = 5 V, I <sub>C</sub> = 40 mA, f = 1 GHz, Z <sub>S</sub> = Z <sub>Sopt</sub> , Z <sub>L</sub> = Z <sub>Lopt</sub>	–	0.7	–	dB
Associated Gain (1)	G <sub>a1</sub>	V <sub>CE</sub> = 5 V, I <sub>C</sub> = 15 mA, f = 1 GHz, Z <sub>S</sub> = Z <sub>Sopt</sub> , Z <sub>L</sub> = 50 Ω	8.0	10.0	–	dB
Associated Gain (2)	G <sub>a2</sub>	V <sub>CE</sub> = 5 V, I <sub>C</sub> = 40 mA, f = 1 GHz, Z <sub>S</sub> = Z <sub>Sopt</sub> , Z <sub>L</sub> = Z <sub>Lopt</sub>	–	11.0	–	dB
Reverse Transfer Capacitance	C <sub>re</sub> <sup>Note 2</sup>	V <sub>CB</sub> = 5 V, I <sub>E</sub> = 0, f = 1 MHz	–	1.1	1.3	pF
Maximum Stable Power Gain	MSG <sup>Note 3</sup>	V <sub>CE</sub> = 5 V, I <sub>C</sub> = 40 mA, f = 1 GHz	10.0	12.0	–	dB
Gain 1 dB Compression Output Power	P <sub>O</sub> (1 dB)	V <sub>CE</sub> = 5 V, I <sub>C</sub> (set) = 40 mA, f = 1 GHz, Z <sub>S</sub> = Z <sub>Sopt</sub> , Z <sub>L</sub> = Z <sub>Lopt</sub>	–	24.0	–	dBm
Output 3rd Order Intercept Point	OIP <sub>3</sub>	V <sub>CE</sub> = 5 V, I <sub>C</sub> (set) = 40 mA, f = 1 GHz, Δf = 1 MHz, Z <sub>S</sub> = Z <sub>Sopt</sub> , Z <sub>L</sub> = Z <sub>Lopt</sub>	–	35.5	–	dBm

Notes: 1. Pulse measurement: PW ≤ 350 μs, Duty Cycle ≤ 2%

2. Collector to base capacitance when the emitter grounded.


3. 
$$MSG = \left| \frac{S_{21}}{S_{12}} \right|$$

**h<sub>FE</sub> CLASSIFICATION**


Rank	FB
Marking	ST
h <sub>FE</sub> Value	200 to 500

**TYPICAL CHARACTERISTICS (T<sub>A</sub> = +25°C, unless otherwise specified)**


**TOTAL POWER DISSIPATION vs. AMBIENT TEMPERATURE**




**REVERSE TRANSFER CAPACITANCE vs. COLLECTOR TO BASE VOLTAGE**




**COLLECTOR CURRENT vs. BASE TO EMITTER VOLTAGE**



**COLLECTOR CURRENT vs. BASE TO EMITTER VOLTAGE**




**COLLECTOR CURRENT vs. COLLECTOR TO EMITTER VOLTAGE**




**Remark** The graphs indicate nominal characteristics.


DC CURRENT GAIN vs. COLLECTOR CURRENT




DC CURRENT GAIN vs. COLLECTOR CURRENT



GAIN BANDWIDTH PRODUCT vs. COLLECTOR CURRENT




GAIN BANDWIDTH PRODUCT vs. COLLECTOR CURRENT




**Remark** The graphs indicate nominal characteristics.


INSERTION POWER GAIN, MAG, MSG vs. FREQUENCY




INSERTION POWER GAIN, MAG, MSG vs. FREQUENCY




INSERTION POWER GAIN, MAG, MSG vs. FREQUENCY




INSERTION POWER GAIN, MAG, MSG vs. FREQUENCY



INSERTION POWER GAIN, MAG, MSG vs. COLLECTOR CURRENT




INSERTION POWER GAIN, MAG, MSG vs. COLLECTOR CURRENT




**Remark** The graphs indicate nominal characteristics.


NOISE FIGURE, ASSOCIATED GAIN vs. COLLECTOR CURRENT




OUTPUT POWER, LINEAR GAIN, COLLECTOR CURRENT vs. INPUT POWER



EACH OUTPUT POWER,  $IM_3$  vs. EACH INPUT POWER



OUTPUT 3RD ORDER INTERCEPT POINT vs. COLLECTOR CURRENT



**Remark** The graphs indicate nominal characteristics.

## S-PARAMETERS

S-parameters and noise parameters are provided on our Web site in a format (S2P) that enables the direct import of the parameters to microwave circuit simulators without the need for keyboard inputs.

Click here to download S-parameters.


[RF and Microwave] → [Device Parameters]

URL <http://www2.renesas.com/microwave/en/download.html>



## PACKAGE DIMENSIONS

3-PIN POWER MINIMOLD (34 PKG) (UNIT: mm)



### PIN CONNECTIONS

1. Emitter
2. Collector
3. Base

<b>Revision History</b>	<b>NESG340034 Data Sheet</b>
-------------------------	------------------------------

Rev.	Date	Description	
		Page	Summary
1.00	Jun 27, 2011	–	First edition issued
2.00	Aug 18, 2011	p.3	<b>ELECTRICAL CHARACTERISTICS</b> DC Current Gain 400 → 500 (MAX.)

All trademarks and registered trademarks are the property of their respective owners.

## Notice

- All information included in this document is current as of the date this document is issued. Such information, however, is subject to change without any prior notice. Before purchasing or using any Renesas Electronics products listed herein, please confirm the latest product information with a Renesas Electronics sales office. Also, please pay regular and careful attention to additional and different information to be disclosed by Renesas Electronics such as that disclosed through our website.
- Renesas Electronics does not assume any liability for infringement of patents, copyrights, or other intellectual property rights of third parties by or arising from the use of Renesas Electronics products or technical information described in this document. No license, express, implied or otherwise, is granted hereby under any patents, copyrights or other intellectual property rights of Renesas Electronics or others.
- You should not alter, modify, copy, or otherwise misappropriate any Renesas Electronics product, whether in whole or in part.
- Descriptions of circuits, software and other related information in this document are provided only to illustrate the operation of semiconductor products and application examples. You are fully responsible for the incorporation of these circuits, software, and information in the design of your equipment. Renesas Electronics assumes no responsibility for any losses incurred by you or third parties arising from the use of these circuits, software, or information.
- When exporting the products or technology described in this document, you should comply with the applicable export control laws and regulations and follow the procedures required by such laws and regulations. You should not use Renesas Electronics products or the technology described in this document for any purpose relating to military applications or use by the military, including but not limited to the development of weapons of mass destruction. Renesas Electronics products and technology may not be used for or incorporated into any products or systems whose manufacture, use, or sale is prohibited under any applicable domestic or foreign laws or regulations.
- Renesas Electronics has used reasonable care in preparing the information included in this document, but Renesas Electronics does not warrant that such information is error free. Renesas Electronics assumes no liability whatsoever for any damages incurred by you resulting from errors in or omissions from the information included herein.
- Renesas Electronics products are classified according to the following three quality grades: "Standard", "High Quality", and "Specific". The recommended applications for each Renesas Electronics product depends on the product's quality grade, as indicated below. You must check the quality grade of each Renesas Electronics product before using it in a particular application. You may not use any Renesas Electronics product for any application categorized as "Specific" without the prior written consent of Renesas Electronics. Further, you may not use any Renesas Electronics product for any application for which it is not intended without the prior written consent of Renesas Electronics. Renesas Electronics shall not be in any way liable for any damages or losses incurred by you or third parties arising from the use of any Renesas Electronics product for an application categorized as "Specific" or for which the product is not intended where you have failed to obtain the prior written consent of Renesas Electronics. The quality grade of each Renesas Electronics product is "Standard" unless otherwise expressly specified in a Renesas Electronics data sheets or data books, etc.  
"Standard": Computers; office equipment; communications equipment; test and measurement equipment; audio and visual equipment; home electronic appliances; machine tools; personal electronic equipment; and industrial robots.  
"High Quality": Transportation equipment (automobiles, trains, ships, etc.); traffic control systems; anti-disaster systems; anti-crime systems; safety equipment; and medical equipment not specifically designed for life support.  
"Specific": Aircraft; aerospace equipment; submersible repeaters; nuclear reactor control systems; medical equipment or systems for life support (e.g. artificial life support devices or systems), surgical implantations, or healthcare intervention (e.g. excision, etc.), and any other applications or purposes that pose a direct threat to human life.
- You should use the Renesas Electronics products described in this document within the range specified by Renesas Electronics, especially with respect to the maximum rating, operating supply voltage range, movement power voltage range, heat radiation characteristics, installation and other product characteristics. Renesas Electronics shall have no liability for malfunctions or damages arising out of the use of Renesas Electronics products beyond such specified ranges.
- Although Renesas Electronics endeavors to improve the quality and reliability of its products, semiconductor products have specific characteristics such as the occurrence of failure at a certain rate and malfunctions under certain use conditions. Further, Renesas Electronics products are not subject to radiation resistance design. Please be sure to implement safety measures to guard them against the possibility of physical injury, and injury or damage caused by fire in the event of the failure of a Renesas Electronics product, such as safety design for hardware and software including but not limited to redundancy, fire control and malfunction prevention, appropriate treatment for aging degradation or any other appropriate measures. Because the evaluation of microcomputer software alone is very difficult, please evaluate the safety of the final products or system manufactured by you.
- Please contact a Renesas Electronics sales office for details as to environmental matters such as the environmental compatibility of each Renesas Electronics product. Please use Renesas Electronics products in compliance with all applicable laws and regulations that regulate the inclusion or use of controlled substances, including without limitation, the EU RoHS Directive. Renesas Electronics assumes no liability for damages or losses occurring as a result of your noncompliance with applicable laws and regulations.
- This document may not be reproduced or duplicated, in any form, in whole or in part, without prior written consent of Renesas Electronics.
- Please contact a Renesas Electronics sales office if you have any questions regarding the information contained in this document or Renesas Electronics products, or if you have any other inquiries.  
(Note 1) "Renesas Electronics" as used in this document means Renesas Electronics Corporation and also includes its majority-owned subsidiaries.  
(Note 2) "Renesas Electronics product(s)" means any product developed or manufactured by or for Renesas Electronics.



### SALES OFFICES

Renesas Electronics Corporation

<http://www.renesas.com>

Refer to "<http://www.renesas.com/>" for the latest and detailed information.

**Renesas Electronics America Inc.**  
2880 Scott Boulevard Santa Clara, CA 95050-2554, U.S.A.  
Tel: +1-408-586-6000, Fax: +1-408-586-6130

**Renesas Electronics Canada Limited**  
1101 Nicholson Road, Newmarket, Ontario L3Y 9C3, Canada  
Tel: +1-905-898-5441, Fax: +1-905-898-3220

**Renesas Electronics Europe Limited**  
Dukes Meadow, Millboard Road, Bourne End, Buckinghamshire, SL8 5FH, U.K  
Tel: +44-1628-585-100, Fax: +44-1628-585-900

**Renesas Electronics Europe GmbH**  
Arcadiastrasse 10, 40472 Düsseldorf, Germany  
Tel: +49-211-65030, Fax: +49-211-6503-1327

**Renesas Electronics (China) Co., Ltd.**  
7th Floor, Quantum Plaza, No.27 ZhiChunLu Haidian District, Beijing 100083, P.R.China  
Tel: +86-10-8235-1155, Fax: +86-10-8235-7679

**Renesas Electronics (Shanghai) Co., Ltd.**  
Unit 204, 205, AZIA Center, No.1233 Lujiazui Ring Rd., Pudong District, Shanghai 200120, China  
Tel: +86-21-5877-1818, Fax: +86-21-6887-7858 / -7898

**Renesas Electronics Hong Kong Limited**  
Unit 1601-1613, 16/F., Tower 2, Grand Century Place, 193 Prince Edward Road West, Mongkok, Kowloon, Hong Kong  
Tel: +852-2886-9318, Fax: +852 2886-9022/9044

**Renesas Electronics Taiwan Co., Ltd.**  
13F, No. 363, Fu Shing North Road, Taipei, Taiwan  
Tel: +886-2-8175-9600, Fax: +886 2-8175-9670

**Renesas Electronics Singapore Pte. Ltd.**  
1 HarbourFront Avenue, #06-10, Keppel Bay Tower, Singapore 098632  
Tel: +65-6213-0200, Fax: +65-6276-8001

**Renesas Electronics Malaysia Sdn.Bhd.**  
Unit 906, Block B, Menara Amcorp, Amcorp Trade Centre, No. 18, Jln Persiaran Barat, 46050 Petaling Jaya, Selangor Darul Ehsan, Malaysia  
Tel: +60-3-7955-9390, Fax: +60-3-7955-9510

**Renesas Electronics Korea Co., Ltd.**  
11F., Samik Lavied' or Bldg., 720-2 Yeoksam-Dong, Kangnam-Ku, Seoul 135-080, Korea  
Tel: +82-2-558-3737, Fax: +82-2-558-5141