

Ferrite Beads

Standard Part Numbers & Data


FBM 0402 SERIES DATA TABLE

Series Part Number	Thickness (mm)	Impedance (Ω) \pm 25% (at 100MHz)	DC resistance (Ω) max.	Rated current (mA) max.
FBM 0402-100 □	0.5 \pm 0.05	10	0.05	500
FBM 0402-300 □	0.5 \pm 0.05	30	0.15	300
FBM 0402-600 □	0.5 \pm 0.05	60	0.20	200
FBM 0402-800 □	0.5 \pm 0.05	80	0.30	200
FBM 0402-121 □	0.5 \pm 0.05	120	0.30	200
FBM 0402-241 □	0.5 \pm 0.05	240	0.50	150
FBM 0402-301 □	0.5 \pm 0.05	300	0.60	100
FBM 0402-471 □	0.5 \pm 0.05	470	0.70	100
FBM 0402-601 □	0.5 \pm 0.05	600	0.70	100
FBM 0402-102 □	0.5 \pm 0.05	1000	0.90	100
FBM 0402-152 □	0.5 \pm 0.05	1500	1.00	100


Venkel Ltd. may also be able to provide custom products to meet specific customer needs. Please consult your sales representative.

FBM 0402 SERIES


FBM0402-100 □




FBM0402-600 □




FBM0402-121 □




FBM0402-300 □



FBM0402-800 □



FBM0402-241 □




All components in this section are RoHS compliant per the EU directives and definitions.


5900 Shepherd Mountain Cove • Austin, TX 78730
 Phone: 512 / 794-0081 • Fax: 512 / 794-0087 • Toll Free: 800 / 950-8365
 e-mail: sales@venkel.com • www.venkel.com

FBM 0402 SERIES


FBM0402-301 □




FBM0402-102 □




FBM0402-471 □



FBM0402-152 □



FBM0402-601 □



Ferrite Beads


Standard Part Numbers & Data

FBM 0603 / 0805 / 1206 SERIES DATA TABLE				
Series Part Number	Thickness (mm)	Impedance (Ω) \pm 25% (at 100MHz)	DC resistance (Ω) max.	Rated current (mA) max.
FBM 0603-400 □	0.5 \pm 0.05	40	0.15	300
FBM 0603-600 □	0.8 \pm 0.15	60	0.15	300
FBM 0603-800 □	0.8 \pm 0.15	80	0.15	300
FBM 0603-121 □	0.8 \pm 0.15	120	0.20	200
FBM 0603-241 □	0.8 \pm 0.15	240	0.30	200
FBM 0603-471 □	0.8 \pm 0.15	470	0.40	200
FBM 0603-601 □	0.8 \pm 0.15	600	0.50	200
FBM 0603-102 □	0.8 \pm 0.15	1000	0.70	100
FBM 0603-152 □	0.8 \pm 0.15	1500	0.80	50
FBM 0603-202 □	0.8 \pm 0.15	2000 (at 70 MHz)	1.20	50
FBM 0805-600 □	0.9 \pm 0.2	60	0.10	800
FBM 0805-800 □	0.9 \pm 0.2	80	0.10	800
FBM 0805-101 □	0.9 \pm 0.2	100	0.10	500
FBM 0805-121 □	0.9 \pm 0.2	120	0.15	500
FBM 0805-151 □	0.9 \pm 0.2	150	0.15	300
FBM 0805-241 □	0.9 \pm 0.2	240	0.25	300
FBM 0805-301 □	0.9 \pm 0.2	300	0.25	300
FBM 0805-471 □	0.9 \pm 0.2	470	0.30	300
FBM 0805-601 □	0.9 \pm 0.2	600	0.30	300
FBM 0805-102 □	0.9 \pm 0.2	1000	0.40	300
FBM 0805-152 □	0.9 \pm 0.2	1500 (at 70 MHz)	0.60	200
FBM 0805-202 □	0.9 \pm 0.2	2000 (at 70 MHz)	0.70	200
FBM 1206-151 □	1.1 \pm 0.2	150	0.20	500
FBM 1206-221 □	1.1 \pm 0.2	220	0.30	400
FBM 1206-301 □	1.1 \pm 0.2	300	0.40	300
FBM 1206-601 □	1.1 \pm 0.2	600	0.50	200
FBM 1206-801 □	1.1 \pm 0.2	800	0.50	200
FBM 1206-102 □	1.1 \pm 0.2	1000	0.50	200
FBM 1206-152 □	1.1 \pm 0.2	1500 (at 70 MHz)	0.70	100


Venkel Ltd. may also be able to provide custom products to meet specific customer needs. Please consult your sales representative.

FBM 0603 SERIES


FBM0603-400 □




FBM0603-121 □




FBM0603-601 □




FBM0603-600 □




FBM0603-241 □




FBM0603-102 □




FBM0603-800 □




FBM0603-471 □



FBM0603-152 □




FBM0603-202 □




Ferrite Beads

FBM 0805 SERIES


FBM0805-600 □




FBM0805-121 □




FBM0805-301 □




FBM0805-800 □




FBM0805-151 □




FBM0805-471 □




FBM0805-101 □



FBM0805-241 □



FBM0805-601 □




All components in this section are RoHS compliant per the EU directives and definitions.


5900 Shepherd Mountain Cove • Austin, TX 78730
 Phone: 512 / 794-0081 • Fax: 512 / 794-0087 • Toll Free: 800 / 950-8365
 e-mail: sales@venkel.com • www.venkel.com

FBM 0805 SERIES


FBM0805-102 □



FBM0805-152 □




FBM0805-202 □




FBM 1206 SERIES


FBM1206-151 □




FBM1206-221 □




FBM1206-301 □




FBM1206-601 □



FBM1206-801 □



FBM1206-102 □



FBM1206-152 □

