



## SGM2032

### Low Power, Low Dropout, RF Linear Regulators

#### GENERAL DESCRIPTION

The SGM2032 series low-power, low-noise, low-dropout, CMOS linear voltage regulators operate from a 2.5V to 5.5V input voltage. They are the perfect choice for low voltage, low power applications. A low ground current makes this part attractive for battery operated power systems. The SGM2032 series also offer low dropout voltage to prolong battery life in portable electronics. Systems requiring a quiet voltage source, such as RF applications, will benefit from the SGM2032 series' ultra low output noise and high PSRR. An external noise bypass capacitor connected to the device's BP pin can further reduce the noise level.

The output voltage is preset to voltages in the range of 0.9V to 5.0V. Other features include a 10nA logic-controlled shutdown mode, output current limit and thermal shutdown protection.

The SGM2032 is available in Green SOT-23-5 and SC70-5 packages. It operates over an ambient temperature range of -40°C to +85°C.

#### FEATURES

- Low Output Noise
- Low Dropout Voltage
- Thermal-Overload Protection
- Output Current Limit
- High PSRR (75dB at 1kHz)
- 10nA Logic-Controlled Shutdown
- Adjustable Output from 0.8V to 5.0V
- Available Fixed Output Voltages: 0.9V, 1.3V, 2.1V, 2.7V, 2.9V, 3.1V, 3.2V, 3.6V, 4.2V and 5.0V
- -40°C to +85°C Operating Temperature Range
- Available in Green SC70-5 and SOT-23-5 Packages

#### APPLICATIONS

Cellular Telephones  
Cordless Telephones  
PCMCIA Cards  
Modems  
MP3 Player  
Hand-Held Instruments  
Palmtop Computers  
Electronic Planners  
Portable/Battery-Powered Equipment



# Low Power, Low Dropout, RF Linear Regulators


**SGM2032**

## PACKAGE/ORDERING INFORMATION

MODEL	V <sub>OUT</sub> (V)	PIN-PACKAGE	ORDERING NUMBER	PACKAGE MARKING	PACKAGE OPTION
SGM2032-0.9	0.9V	SOT-23-5	SGM2032-0.9YN5G/TR	S60XX	Tape and Reel, 3000
SGM2032-0.9	0.9V	SC70-5	SGM2032-0.9YC5G/TR	S61XX	Tape and Reel, 3000
SGM2032-1.3	1.3V	SC70-5	SGM2032-1.3YC5G/TR	YJ13	Tape and Reel, 3000
SGM2032-1.3	1.3V	SOT-23-5	SGM2032-1.3YN5G/TR	YJ13	Tape and Reel, 3000
SGM2032-2.1	2.1V	SC70-5	SGM2032-2.1YC5G/TR	YJ21	Tape and Reel, 3000
SGM2032-2.1	2.1V	SOT-23-5	SGM2032-2.1YN5G/TR	YJ21	Tape and Reel, 3000
SGM2032-2.7	2.7V	SC70-5	SGM2032-2.7YC5G/TR	YJ27	Tape and Reel, 3000
SGM2032-2.7	2.7V	SOT-23-5	SGM2032-2.7YN5G/TR	YJ27	Tape and Reel, 3000
SGM2032-2.9	2.9V	SC70-5	SGM2032-2.9YC5G/TR	YJ29	Tape and Reel, 3000
SGM2032-2.9	2.9V	SOT-23-5	SGM2032-2.9YN5G/TR	YJ29	Tape and Reel, 3000
SGM2032-3.1	3.1V	SC70-5	SGM2032-3.1YC5G/TR	YJ31	Tape and Reel, 3000
SGM2032-3.1	3.1V	SOT-23-5	SGM2032-3.1YN5G/TR	YJ31	Tape and Reel, 3000
SGM2032-3.2	3.2V	SC70-5	SGM2032-3.2YC5G/TR	YJ32	Tape and Reel, 3000
SGM2032-3.2	3.2V	SOT-23-5	SGM2032-3.2YN5G/TR	YJ32	Tape and Reel, 3000
SGM2032-3.6	3.6V	SC70-5	SGM2032-3.6YC5G/TR	YJ36	Tape and Reel, 3000
SGM2032-3.6	3.6V	SOT-23-5	SGM2032-3.6YN5G/TR	YJ36	Tape and Reel, 3000
SGM2032-4.2	4.2V	SC70-5	SGM2032-4.2YC5G/TR	YJ42	Tape and Reel, 3000
SGM2032-4.2	4.2V	SOT-23-5	SGM2032-4.2YN5G/TR	YJ42	Tape and Reel, 3000
SGM2032-5.0	5.0V	SC70-5	SGM2032-5.0YC5G/TR	YJ50	Tape and Reel, 3000
SGM2032-5.0	5.0V	SOT-23-5	SGM2032-5.0YN5G/TR	YJ50	Tape and Reel, 3000
SGM2032-ADJ	adjustable	SOT-23-5	SGM2032-ADJYN5G/TR	S5EXX	Tape and Reel, 3000
SGM2032-ADJ	adjustable	SC70-5	SGM2032-ADJYC5G/TR	S5FXX	Tape and Reel, 3000

### ORDER NUMBER

SGM2032 - X X X G / TR




0.9	0.9V
1.3	1.3V
:	:
3.6	3.6V
4.2	4.2V
5.0	5.0V
ADJ	adjustable

## SGM2032

# Low Power, Low Dropout, RF Linear Regulators

## PIN CONFIGURATIONS (TOP VIEW)



NOTE: Orientation of top mark determines pin1 location. Read the top product code mark left to right, pin1 is the lower left pin.

## CAUTION

This integrated circuit can be damaged by ESD if you don't pay attention to ESD protection. SGMICRO recommends that all integrated circuits be handled with appropriate precautions. Failure to observe proper handling and installation procedures can cause damage. ESD damage can range from subtle performance degradation to complete device failure. Precision integrated circuits may be more susceptible to damage because very small parametric changes could cause the device not to meet its published specifications.

SGMICRO reserves the right to make any change in circuit design, specification or other related things if necessary without notice at any time. Please contact SGMICRO sales office to get the latest datasheet.

## PIN DESCRIPTION

PIN	NAME	FUNCTION
1	IN	Regulator Input. Supply voltage can range from 2.5V to 5.5V. Bypass with a 1 $\mu$ F capacitor to GND.
2	GND	Ground.
3	EN	Shutdown Input. A logic low reduces the supply current to 10nA. Connect to IN for normal operation.
4	BP	Reference-Noise Bypass (fixed voltage version only). Bypass with a low-leakage 0.01 $\mu$ F ceramic capacitor for reduced noise at the output.
	FB	Feedback Pin (adjustable voltage version only). This is used to set the output voltage of the device.
5	OUT	Regulator Output.

# Low Power, Low Dropout, RF Linear Regulators

## SGM2032

### ELECTRICAL CHARACTERISTICS

( $V_{IN} = V_{OUT\ (NOMINAL)} + 0.5V$  or  $2.5V$ , whichever is greater, Full =  $-40^{\circ}C$  to  $+85^{\circ}C$ , unless otherwise noted.)

PARAMETER	SYMBOL	CONDITIONS	TEMP	MIN	TYP	MAX	UNITS
Input Voltage	$V_{IN}$		$+25^{\circ}C$	2.5		5.5	V
Output Voltage Accuracy		$I_{OUT} = 0.1mA$	$+25^{\circ}C$	-2		+2	%
Maximum Output Current		SOT-23-5	$+25^{\circ}C$	300			mA
		$V_{OUT} < 1V$ , SC70-5		120			
		$1V \leq V_{OUT} \leq 2V$ , SC70-5		150			
		$V_{OUT} > 2V$ , SC70-5		250			
Current Limit	$I_{LIM}$		$+25^{\circ}C$	310	500		mA
Ground Pin Current	$I_Q$	No load, EN = 2V	$+25^{\circ}C$		120	220	$\mu A$
Dropout Voltage <sup>(1)</sup>		$I_{OUT} = 1mA$	$+25^{\circ}C$		0.9		mV
		$I_{OUT} = 300mA$			270	400	
Line Regulation	$\Delta V_{LNR}$	$V_{IN} = 2.5V$ or $(V_{OUT} + 0.5V)$ to $5.5V$ , $I_{OUT} = 1mA$	$+25^{\circ}C$		0.02	0.05	%/V
Load Regulation	$\Delta V_{LDR}$	$I_{OUT} = 0.1mA$ to $300mA$ , $C_{OUT} = 1\mu F$ , $V_{OUT} > 2V$	$+25^{\circ}C$		0.002	0.005	%/ $mA$
		$I_{OUT} = 0.1mA$ to $300mA$ , $C_{OUT} = 1\mu F$ , $V_{OUT} \leq 2V$			0.004	0.008	
Output Voltage Noise	$e_n$	$f = 10Hz$ to $100kHz$ , $C_{BP} = 0.01\mu F$ , $C_{OUT} = 10\mu F$ , Fixed Output of $0.9V$	$+25^{\circ}C$		30		$\mu V_{RMS}$
Power Supply Rejection Ratio	PSRR	$C_{BP} = 0.1\mu F$ , $I_{LOAD} = 50mA$ , $f = 217Hz$	$+25^{\circ}C$		80		dB
		$C_{OUT} = 1\mu F$ , Fixed Output of $0.9V$	$+25^{\circ}C$		75		dB
<b>SHUTDOWN <sup>(2)</sup></b>							
EN Input Threshold	$V_{IH}$	$V_{IN} = 2.5V$ to $5.5V$ , $V_{EN} = -0.3V$ to $V_{IN}$	Full	1.5			V
	$V_{IL}$		Full			0.3	
EN Input Bias Current	$I_{B(SHDN)}$	EN = 0V and EN = 5.5V	$+25^{\circ}C$		0.01	1	$\mu A$
Shutdown Supply Current	$I_{Q(SHDN)}$	EN = 0.3V	$+25^{\circ}C$		0.01	1	$\mu A$
Shutdown Exit Delay <sup>(3)</sup>		$C_{OUT} = 1\mu F$ , No Load	$+25^{\circ}C$		30		$\mu s$
<b>THERMAL PROTECTION</b>							
Thermal Shutdown Temperature	$T_{SHDN}$				150		$^{\circ}C$
Thermal Shutdown Hysteresis	$\Delta T_{SHDN}$				15		$^{\circ}C$



#### NOTES:

- The dropout voltage is defined as  $V_{IN} - V_{OUT}$ , when  $V_{OUT}$  is 100mV below the value of  $V_{OUT}$  for  $V_{IN} = V_{OUT} + 0.5V$  (only applicable for  $V_{OUT} = +2.5V$  to  $+5.0V$ ).
- $V_{EN} = -0.3V$  to  $V_{IN}$
- Time needed for  $V_{OUT}$  to reach 90% of final value.

## SGM2032

# Low Power, Low Dropout, RF Linear Regulators

## TYPICAL APPLICATION CIRCUITS









Standard 1% Resistor Values for Common  
Output Voltages of Adjustable Voltage Version

V <sub>OUT</sub> (V)	R <sub>1</sub> (kΩ)	R <sub>2</sub> (kΩ)
0.8	No Need	40.2
1.0	10.5	40.2
1.5	35.7	40.2
1.8	51.1	40.2
2.5	86.6	40.2
2.7	95.3	40.2
2.85	97.6	37.4
2.9	97.6	37.0
3.0	97.6	35.7
3.6	97.6	28.0

NOTE: V<sub>OUT</sub> = (R<sub>1</sub> + R<sub>2</sub>)/R<sub>2</sub> × 0.8

## TYPICAL PERFORMANCE CHARACTERISTICS

$V_{IN} = V_{OUT\ (NOMINAL)} + 0.5V$  or  $2.5V$  (whichever is greater),  $C_{IN} = 1\mu F$ ,  $C_{OUT} = 1\mu F$ ,  $C_{BP} = 0.01\mu F$ ,  $T_A = +25^\circ C$ , unless otherwise noted.




# Low Power, Low Dropout, RF Linear Regulators

## SGM2032


### TYPICAL PERFORMANCE CHARACTERISTICS

$V_{IN} = V_{OUT\ (NOMINAL)} + 0.5V$  or  $2.5V$  (whichever is greater),  $C_{IN} = 1\mu F$ ,  $C_{OUT} = 1\mu F$ ,  $C_{BP} = 0.01\mu F$ ,  $T_A = +25^\circ C$ , unless otherwise noted.


Power Supply Rejection Ratio vs. Frequency




Ground Pin Current vs. Temperature




Output Voltage Accuracy vs. Temperature




Output Voltage vs. Load Current



Current Limit vs. Temperature



Ground Pin Current vs. Load Current




# Low Power, Low Dropout, RF Linear Regulators

**SGM2032**


## TYPICAL PERFORMANCE CHARACTERISTICS

$V_{IN} = V_{OUT\ (NOMINAL)} + 0.5V$  or  $2.5V$  (whichever is greater),  $C_{IN} = 1\mu F$ ,  $C_{OUT} = 1\mu F$ ,  $C_{BP} = 0.01\mu F$ ,  $T_A = +25^\circ C$ , unless otherwise noted.


Ground Pin Current vs. Input Voltage



Dropout Voltage vs. Load Current






Output Voltage vs. Input Voltage





## APPLICATION NOTE

When LDO is used in handheld products, attention must be paid to voltage spikes which could damage SGM2032. In such applications, voltage spikes will be generated at charger interface and  $V_{BUS}$  pin of USB interface when charger adapters and USB equipments are hot-plugged. Besides this, handheld products will be tested on the production line without battery. Test engineer will apply power from the connector pin which connects with positive pole of the battery. When external power supply is turned on suddenly, the voltage spikes will be generated at the battery connector. The voltage spikes will be very high, and it always exceeds the absolute maximum input voltage (6.0V) of LDO. In order to get robust design, design engineer needs to clear up this voltage spike. Zener diode is a cheap and effective solution to eliminate such voltage spike. For example, BZM55B5V6 is a 5.6V small package Zener diode which can be used to remove voltage spikes in cell phone designs. The schematic is shown below.



**SGM2032****Low Power, Low Dropout,  
RF Linear Regulators****PACKAGE OUTLINE DIMENSIONS****SC70-5**



RECOMMENDED LAND PATTERN (Unit: mm)





Symbol	Dimensions In Millimeters		Dimensions In Inches	
	MIN	MAX	MIN	MAX
A	0.900	1.100	0.035	0.043
A1	0.000	0.100	0.000	0.004
A2	0.900	1.000	0.035	0.039
b	0.150	0.350	0.006	0.014
c	0.080	0.150	0.003	0.006
D	2.000	2.200	0.079	0.087
E	1.150	1.350	0.045	0.053
E1	2.150	2.450	0.085	0.096
e	0.65 TYP		0.026 TYP	
e1	1.300 BSC		0.051 BSC	
L	0.525 REF		0.021 REF	
L1	0.260	0.460	0.010	0.018
θ	0°	8°	0°	8°

## PACKAGE OUTLINE DIMENSIONS

## SOT-23-5




RECOMMENDED LAND PATTERN (Unit: mm)




Symbol	Dimensions In Millimeters		Dimensions In Inches	
	MIN	MAX	MIN	MAX
A	1.050	1.250	0.041	0.049
A1	0.000	0.100	0.000	0.004
A2	1.050	1.150	0.041	0.045
b	0.300	0.500	0.012	0.020
c	0.100	0.200	0.004	0.008
D	2.820	3.020	0.111	0.119
E	1.500	1.700	0.059	0.067
E1	2.650	2.950	0.104	0.116
e	0.950 BSC		0.037 BSC	
e1	1.900 BSC		0.075 BSC	
L	0.300	0.600	0.012	0.024
θ	0°	8°	0°	8°

## TAPE AND REEL INFORMATION

## REEL DIMENSIONS




## TAPE DIMENSIONS



NOTE: The picture is only for reference. Please make the object as the standard.

## KEY PARAMETER LIST OF TAPE AND REEL

Package Type	Reel Diameter	Reel Width W1 (mm)	A0 (mm)	B0 (mm)	K0 (mm)	P0 (mm)	P1 (mm)	P2 (mm)	W (mm)	Pin1 Quadrant
SC70-5	7"	9.5	2.25	2.55	1.20	4.0	4.0	2.0	8.0	Q3
SOT-23-5	7"	9.5	3.2	3.2	1.4	4.0	4.0	2.0	8.0	Q3

**CARTON BOX DIMENSIONS**

NOTE: The picture is only for reference. Please make the object as the standard.

**KEY PARAMETER LIST OF CARTON BOX**

Reel Type	Length (mm)	Width (mm)	Height (mm)	Pizza/Carton
7" (Option)	368	227	224	8
7"	442	410	224	18