

□ MN102H85K

Type	MN102H85K
ROM (×16-bit)	256 K
RAM (×16-bit)	8 K
Package (Conventional Package)	SDIP064-P-0750C *Lead-free (SDIP064-P-0750)
Minimum Instruction Execution Time	83 ns (at 3.0 V to 3.6 V, 12 MHz)
Interrupts	External (6 lines) Internal (30 lines) : Timer × 11, A/D × 1, Undefined command × 1, RESET × 1, OSD × 2, Serial × 4, I ² C × 1, Caption × 4, Remote control × 1, Address coincidence × 4
Timer Counter	8-bit timer × 4 16-bit timer × 2 Watchdog timer: 17-bit × 1
Serial Interface	I ² C × 1: for multimaster mode, bus line (output) has 2 systems Sync serial / I ² C (master) / UART × 2
Caption	• Built-in sync separator × 2
I/O Pins	I/O 50 • Common use
A/D Inputs	8-bit × 12-ch. (with S/H)
D/A Outputs	4-bit × 4-ch. (analog R, G, B, YM output)
PWM	8-bit × 7-ch.
Special Ports	Remote control reception
CRTC	3-layer display (graphics, characters, splits)
Notes	Remote control input discriminant circuit built-in

Electrical Characteristics


D/A characteristics

Parameter	Symbol	Condition	Limit			Unit
			min	typ	max	
D/A full-scale output current	IFS	RL = 200 Ω, VREF = 1.2 V, RIREF = 1.2 kΩ	4.5	5.0	5.5	mA
D/A output voltage setting range	VO	RL = 200 Ω, VREF = 1.2 V, RIREF = 1.2 kΩ	0.9		1.1	V
D/A non-linear error	NLE	RL = 200 Ω, VREF = 1.2 V, RIREF = 1.2 kΩ			± 0.5	LSB
D/A differential non-linear error	DNLE	RL = 200 Ω, VREF = 1.2 V, RIREF = 1.2 kΩ			± 0.5	LSB
D/A channel interval error	IFS	VREF = 1.2 V, RIREF = 1.2 kΩ, Error from 4-channel average IFS			± 5	%

(Ta = 25°C, VDD = AVDD = 3.3 V, VSS = 0 V, fosc = 4 MHz)

Pin Assignment

() : Conventional Package



SDIP064-P-0750C *Lead-free
(SDIP064-P-0750)

*1: 5 V dielectric Nch open drain output pin

*2 : MN102H85K (VDD), MN102HF85K (VPP)

Support Tool

In-circuit Emulator	PX-ICE102H85-SDIP064-P-0750	
Flash Memory Built-in Type	Type	MN102HF85K
	ROM (× 16-bit)	256 K
	RAM (× 16-bit)	8 K
	Minimum instruction execution time	83 ns (at 3.0 V to 3.6 V, 12 MHz)
	Package	SDIP064-P-0750C *Lead-free
	(Conventional Package)	(SDIP064-P-0750)

Request for your special attention and precautions in using the technical information and semiconductors described in this material

- (1) An export permit needs to be obtained from the competent authorities of the Japanese Government if any of the products or technologies described in this material and controlled under the "Foreign Exchange and Foreign Trade Law" is to be exported or taken out of Japan.
- (2) The technical information described in this material is limited to showing representative characteristics and applied circuits examples of the products. It neither warrants non-infringement of intellectual property right or any other rights owned by our company or a third party, nor grants any license.
- (3) We are not liable for the infringement of rights owned by a third party arising out of the use of the product or technologies as described in this material.
- (4) The products described in this material are intended to be used for standard applications or general electronic equipment (such as office equipment, communications equipment, measuring instruments and household appliances).
Consult our sales staff in advance for information on the following applications:
 - Special applications (such as for airplanes, aerospace, automobiles, traffic control equipment, combustion equipment, life support systems and safety devices) in which exceptional quality and reliability are required, or if the failure or malfunction of the products may directly jeopardize life or harm the human body.
 - Any applications other than the standard applications intended.
- (5) The products and product specifications described in this material are subject to change without notice for modification and/or improvement. At the final stage of your design, purchasing, or use of the products, therefore, ask for the most up-to-date Product Standards in advance to make sure that the latest specifications satisfy your requirements.
- (6) When designing your equipment, comply with the guaranteed values, in particular those of maximum rating, the range of operating power supply voltage, and heat radiation characteristics. Otherwise, we will not be liable for any defect which may arise later in your equipment.
Even when the products are used within the guaranteed values, take into the consideration of incidence of break down and failure mode, possible to occur to semiconductor products. Measures on the systems such as redundant design, arresting the spread of fire or preventing glitch are recommended in order to prevent physical injury, fire, social damages, for example, by using the products.
- (7) When using products for which damp-proof packing is required, observe the conditions (including shelf life and amount of time let standing of unsealed items) agreed upon when specification sheets are individually exchanged.
- (8) This material may be not reprinted or reproduced whether wholly or partially, without the prior written permission of Matsushita Electric Industrial Co., Ltd.