

□ MN103S927, MN103S92A

Type	MN103S927	MN103S92A (under development)						
Internal ROM	16K-byte	32 K-byte						
Internal RAM	2K-byte							
Package	LQFP064-P-1414 *Lead-free							
Minimum Instruction Execution Time	25 ns (at 3.0 V to 3.6 V, 10 MHz) *at internal 4 times oscillation used							
Interrupts	<ul style="list-style-type: none"> • 8 external interrupts • 18 internal interrupts (watch dog timer, timer, serial I/F, PWM, A/D, system error) 							
Timer Counter	8-bit timer × 4 Timer 0 to 3: Interval timer, Event counter, Cascading connectable 16-bit timer × 2 Timer 8: Interval timer, Event counter, PWM output (6 pins simultaneous output are available), Double buffer Timer 11: Interval timer, Double buffer, Start synchronized with 3-phase PWM are available Watch dog timer							
Serial Interface	UART (full duplex) / synchronous interfaces selective × 1 Serial 2: 1-bit to 8-bit transmission (synchronous), 2 and 3 channel type selectable (synchronous)							
I/O Pins	<table border="1"> <tr> <td>I/O</td> <td>41</td> <td>Exclusive × 11, selective × 30</td> </tr> <tr> <td>Input</td> <td>8</td> <td>Selective × 8</td> </tr> </table>	I/O	41	Exclusive × 11, selective × 30	Input	8	Selective × 8	
I/O	41	Exclusive × 11, selective × 30						
Input	8	Selective × 8						
A/D Inputs	10-bit × 3 unit, 2 inputs × 1, 6 inputs × 1 Simultaneous conversion of 2 series are available, With S/H, Conversion start synchronized with 3-phase PWM or timer 11 are available							
Motor Control PWM	16-bit 3-phase PWM × 1 Minimum resolution: 50 ns Triangular waveform or jigsaw waveform dead time setup, Double buffer, Output polar switching is available, PWM output pin protect function							


Electrical Characteristics

A/D converter characteristics

Parameter	Symbol	Condition	Limit			Unit
			min	typ	max	
Non-linear error		10-bit			±3	LSB
A/D conversion time	tAD		1.5			μs
Analog input voltage	VIA		VSS		VDD	V

(Ta = 25°C, VDD = 3.0 V, VSS = 0 V)

Pin Assignment



LQFP064-P-1414 *Lead-free

Support Tool

In-circuit Emulator	PX-ICE-103S92	
On board Debugger	PX-ODB103-DO	
Flash Memory Built-in Type	Type	MN103SF92G
	ROM	128K-byte
	RAM	4K-byte
	Minimum instruction execution time	25 ns (at 3.0 V to 3.6 V, 10 MHz)
	Package	LQFP064-P-1414A *Lead-free

Request for your special attention and precautions in using the technical information and semiconductors described in this material

- (1) An export permit needs to be obtained from the competent authorities of the Japanese Government if any of the products or technical information described in this material and controlled under the "Foreign Exchange and Foreign Trade Law" is to be exported or taken out of Japan.
- (2) The technical information described in this material is limited to showing representative characteristics and applied circuits examples of the products. It neither warrants non-infringement of intellectual property right or any other rights owned by our company or a third party, nor grants any license.
- (3) We are not liable for the infringement of rights owned by a third party arising out of the use of the technical information as described in this material.
- (4) The products described in this material are intended to be used for standard applications or general electronic equipment (such as office equipment, communications equipment, measuring instruments and household appliances).
Consult our sales staff in advance for information on the following applications:
 - Special applications (such as for airplanes, aerospace, automobiles, traffic control equipment, combustion equipment, life support systems and safety devices) in which exceptional quality and reliability are required, or if the failure or malfunction of the products may directly jeopardize life or harm the human body.
 - Any applications other than the standard applications intended.
- (5) The products and product specifications described in this material are subject to change without notice for modification and/or improvement. At the final stage of your design, purchasing, or use of the products, therefore, ask for the most up-to-date Product Standards in advance to make sure that the latest specifications satisfy your requirements.
- (6) When designing your equipment, comply with the guaranteed values, in particular those of maximum rating, the range of operating power supply voltage, and heat radiation characteristics. Otherwise, we will not be liable for any defect which may arise later in your equipment.
Even when the products are used within the guaranteed values, take into the consideration of incidence of break down and failure mode, possible to occur to semiconductor products. Measures on the systems such as redundant design, arresting the spread of fire or preventing glitch are recommended in order to prevent physical injury, fire, social damages, for example, by using the products.
- (7) When using products for which damp-proof packing is required, observe the conditions (including shelf life and amount of time let standing of unsealed items) agreed upon when specification sheets are individually exchanged.
- (8) This material may be not reprinted or reproduced whether wholly or partially, without the prior written permission of Matsushita Electric Industrial Co., Ltd.