



## Features

- Single power can operate at 2.4V through 6.0V.
- Current output could drive 8 ohm speaker with a transistor, Vout could drive buzzer directly.
- The voice content is stored up to 43 seconds at 5.8 KHz (40000h) for S6605 and can be separated to 128 sections. See next page for other device's data.
- Duration of each section can be different and is multiples of 100h.
- Total duration of all 128 sections with mute is up to 96 seconds (80000h).
- The voice content can be accessed in "Sentence" type on KeyBoard (KBD) and Matrix(MTX) modes. Up to 50 Sentences for KeyBoard, 56 Sentences for Matrix modes.
- Each sentence is composed of one or more than one section(s).
- Automatic power down .
- Three addressing interface modes are provided for versatile applications: CPU, KBD and MTX.
- KeyBoard addressing mode:
  - a. 50 sentences can be accessed by 15 addressing input dual-tree type trigger.
  - b. Sentence is numbered by 00 through 49.
  - c. 5 input pins on D-tree (D0-D4) tells the 1st digit (0 through 4), another 10 input pins on S-tree (S0-S9) tells the 2nd digit (0 through 9). By these two digits,all 50 sentences can be accessed.
  - d. With 2nd digit only also can access a sentence.
  - e. Section is located and numbered by 0 through 127.
  - f. Total section number of all sentences is up to 256.
- Matrix addressing mode:
  - a. 56 sentences can be accessed by 8x7 wiring matrix.
  - b. Sentence is numbered by 00 through 55.
  - c. Section is located and numbered by 0 through 127.
  - d. Total section number of all sentences is up to 256.
- CPU addressing mode:
  - a. 128 sections can be accessed by 7 address bits with an enable strobe trigger.
  - b. Section is located and numbered by 00 through 127 .
- Power on trigger play is available by bonding VSS and trigger together.
- A dedicate LED output pin with 6 Hz flash is provided to tell the audio status.
- Playall function (OKY) plays all up to 64 defined sentences one by one by single trigger.
- Playnext (sequential) function (OKY) : one trigger plays next sentence of up to 64 defined sentences circularly.
- Random-play function (OKY) : one trigger plays one of 64 defined sentences randomly.
- Continue sequence(PLAYNEXT):The first OKY trigger after any addressing will keep current sequence continuously.
- Home sequence(PLAYNEXT):The first OKY trigger after any addressing will return the sequence to the first sentence.
- Automatically ramp up & ramp down.
- Sound Sentence & quality could be emulated on 9009 board.

See 27-page data sheet PID 248\*\*\* 08/96 for details which belongs to MSS6605.

Taiwan  
#1, Creation Road I,  
Science - based Industrial Park,  
Hsinchu, 30077  
Taiwan, ROC  
"audio\_reply @ccmail.mosel.com.tw"  
TEL: 886-3-5770055  
FAX: 886-3-5772788  
FAX: 886-3-5784732

Taipei  
7F, #102 Sec. 3,  
Ming Chung E. Road,  
Taipei,105  
Taiwan, ROC  
TEL: 886-2-5451213  
FAX: 886-2-5451214

Hongkong  
#19 Dai Fu Street,  
Taipo Industrial Estate,  
Taipo, N.T.  
Hongkong  
TEL: 852-2388-8277(MKO)  
TEL: 852-2665-4883  
FAX: 852-2664-2406  
FAX: 852-2770-8011(MKO)

U.S.A.  
#3910 North First Street,  
San Jose,  
CA. 65134-1501  
U.S.A.  
TEL: 1-408-433-6000  
FAX: 1-408-433-0952