

TOSHIBA CMOS Digital Integrated Circuit Silicon Monolithic

TC74LCXR164245FT

16-Bit Dual Supply Bus Transceiver with Series Resistor


The TC74LCXR164245FT is a dual supply, advanced high-speed CMOS 16-bit dual supply voltage interface bus transceiver fabricated with silicon gate CMOS technology.

Designed for use as an interface between a 5-V bus and a 3.3-V or 2.5-V bus in mixed 5-V/3.3-V or 2.5-V supply systems, it achieves high-speed operation while maintaining the CMOS low power dissipation.

It is intended for 2 way asynchronous communication between data busses. The direction of data transmission is determined by the level of the DIR input. The enable input (\overline{OE}) can be used to disable the device so that the busses are effectively isolated. The B-port interfaces with the 5-V bus, the A-port with the 3.3-V or 2.5-V-bus.

The 26- Ω series resistor helps reducing output overshoot and undershoot without external resistor.

All inputs are equipped with protection circuits against static discharge or transient excess voltage.



Weight: 0.25 g (typ.)


Features

- Bidirectional interface between 5 V and 3.3 V or 2.5 V buses
- 26- Ω series resistors on outputs
- High-speed: $t_{pd} = 6.8$ ns (max)
($V_{CCB} = 5.0 \pm 0.5$ V/ $V_{CCA} = 3.3 \pm 0.3$ V, $T_a = -40$ to 85°C)
- Low power dissipation: $I_{CC} = 80$ μA (max) ($T_a = -40$ to 85°C)
- Symmetrical output impedance: $I_{OUTB} = \pm 12$ mA (min)
 $I_{OUTA} = \pm 12$ mA (min)
($V_{CCB} = 4.5$ V/ $V_{CCA} = 3.0$ V)
- Power-down protection is provided on all inputs and outputs.
- Allows A port and V_{CCA} to float simultaneously when \overline{OE} is "H"
- Latch-up performance: ± 500 mA
- Package: TSSOP (thin shrink small outline package)


Note 1: Do not apply a signal to any bus pins when it is in the output mode. Damage may result.

All floating (high impedance) bus pins must have their input fixed by means of pull-up or pull-down resistors.

Pin Assignment (top view)



IEC Logic Symbol



Truth Table



Inputs		Function		Outputs
$\overline{1OE}$	1DIR	Bus 1A1-1A8	Bus 1B1-1B8	
L	L	Output	Input	A = B
L	H	Input	Output	B = A
H	X	Z		Z

Inputs		Function		Outputs
$\overline{2OE}$	2DIR	Bus 2A1-2A8	Bus 2B1-2B8	
L	L	Output	Input	A = B
L	H	Input	Output	B = A
H	X	Z		Z

X: Don't care

Z: High impedance

Block Diagram



Maximum Ratings

Characteristics	Symbol	Rating	Unit
Power supply voltage (Note 2)	V_{CCB}	-0.5 to 7.0	V
	V_{CCA}	-0.5 to $V_{CCB} + 0.5$	
DC input voltage (DIR, \overline{OE})	V_{IN}	-0.5 to 7.0	V
DC bus I/O voltage	$V_{I/OB}$	-0.5 to 7.0 (Note 3)	V
		-0.5 to $V_{CCB} + 0.5$ (Note 4)	
	$V_{I/OA}$	-0.5 to 7.0 (Note 3)	
		-0.5 to $V_{CCA} + 0.5$ (Note 4)	
Input diode current	I_{IK}	-50	mA
Output diode current	$I_{I/OK}$	± 50 (Note 5)	mA
DC output current	I_{OUTB}	± 50	mA
	I_{OUTA}	± 50	
DC V_{CC} /ground current per supply pin	I_{CCB}	± 100	mA
	I_{CCA}	± 100	
Power dissipation	P_D	400	mW
Storage temperature	T_{stg}	-65 to 150	$^{\circ}C$

Note 2: $V_{CCB} > V_{CCA}$

Don't supply a voltage to V_{CCA} terminal when V_{CCB} is in the off-state.

Note 3: OFF state

Note 4: High or low state. I_{OUT} absolute maximum rating must be observed.

Note 5: $V_{OUT} < GND, V_{OUT} > V_{CC}$

Recommended Operating Range

Characteristics	Symbol	Rating	Unit
Power supply voltage	V_{CCB}	4.5 to 5.5	V
	V_{CCA}	2.3 to 3.6	
Input voltage (DIR, \overline{OE})	V_{IN}	0 to 5.5	V
Bus I/O voltage	V_{IOB}	0 to 5.5 (Note 6)	V
		0 to V_{CCB} (Note 7)	
	V_{IOA}	0 to 5.5 (Note 6)	
		0 to V_{CCA} (Note 7)	
Output current	I_{OUTB}	± 12 (Note 8)	mA
		± 12 (Note 9)	
	I_{OUTA}	± 4 (Note 10)	
Operating temperature	T_{opr}	-40 to 85	°C
Input rise and fall time	dt/dv	0 to 10 (Note 11)	ns/V

Note 6: OFF state

Note 7: High or low state

Note 8: $V_{CCB} = 4.5$ to 5.5 V

Note 9: $V_{CCA} = 3.0$ to 3.6 V

Note 10: $V_{CCA} = 2.3$ to 2.7 V

Note 11: $V_{INB} = 0.8$ to 2.0 V, $V_{CCB} = 5.0$ V
 $V_{INA} = 0.8$ to 2.0 V, $V_{CCA} = 3.0$ V

Electrical Characteristics

DC Characteristics

Characteristics	Symbol	Test Condition	V _{CCB} (V)	V _{CCA} (V)	Ta = -40 to 85°C		Unit	
					Min	Max		
H-level input voltage	V _{IHB}	DIR, \overline{OE} , Bn	5.0 ± 0.5	2.3 to 3.6	2.0	—	V	
	V _{IHA}	An	5.0 ± 0.5	2.5 ± 0.2	1.7	—		
				5.0 ± 0.5	3.3 ± 0.3	2.0	—	
L-level input voltage	V _{ILB}	DIR, \overline{OE} , Bn	5.0 ± 0.5	2.3 to 3.6	—	0.8	V	
	V _{IHA}	An	5.0 ± 0.5	2.5 ± 0.2	—	0.7		
				5.0 ± 0.5	3.3 ± 0.3	—	0.8	
H-level output voltage	V _{OHB}	V _{IHA} = V _{IHA} or V _{IHA}	I _{OHB} = -100 μA	5.0 ± 0.5	2.3 to 3.6	V _{CCB} - 0.2	—	V
			I _{OHB} = -12 mA	4.5	2.3 to 3.6	3.8	—	
	V _{OHA}	V _{IHB} = V _{IHB} or V _{IHB}	I _{OHA} = -100 μA	5.0 ± 0.5	2.3 to 3.6	V _{CCA} - 0.2	—	
			I _{OHA} = -12 mA	5.0 ± 0.5	3.0	2.2	—	
		I _{OHA} = -4 mA	5.0 ± 0.5	2.3	1.8	—		
L-level output voltage	V _{OLB}	V _{IHA} = V _{IHA} or V _{IHA}	I _{OLB} = 100 μA	5.0 ± 0.5	2.3 to 3.6	—	0.2	V
			I _{OLB} = 12 mA	4.5	2.3 to 3.6	—	0.7	
	V _{OLA}	V _{IHB} = V _{IHB} or V _{IHB}	I _{OLA} = 100 μA	5.0 ± 0.5	2.3 to 3.6	—	0.2	
			I _{OLA} = 12 mA	5.0 ± 0.5	3.0	—	0.8	
		I _{OLA} = 4 mA	5.0 ± 0.5	2.3	—	0.6		
3-state output OFF state current	I _{OZB}	V _{IN} = V _{IHB} or V _{IHB} V _{I/OB} = 0 to 5.5 V	5.0 ± 0.5	2.3 to 3.6	—	±5.0	μA	
	I _{OZA}	V _{IN} = V _{IHB} or V _{IHB} V _{I/OA} = 0 to 5.5 V	5.0 ± 0.5	2.3 to 3.6	—	±5.0		
Input leakage current	I _{IN}	V _{IN} (DIR, \overline{OE}) = 0 to 5.5 V	5.5	3.6	—	±5.0	μA	
Power-off leakage current	I _{OFF}	V _{IHA} /V _{IHB} = 5.5 V	0	0	—	10	μA	
Quiescent supply current	I _{CCB1}	V _{I/OA} = Open, V _{CCA} = Open V _{OE} = V _{CCB} , DIR = GND	5.5	Open	—	80	μA	
	I _{CCB2}	V _{IHA} = V _{CCA} or GND V _{IHB} = V _{CCB} or GND	5.5	3.6	—	80		
	I _{CCA}	V _{IHA} = V _{CCA} or GND V _{IHB} = V _{CCB} or GND	5.5	3.6	—	50		
	I _{CCTB}	V _{IHB} = 3.4 V per input	5.5	2.3 to 3.6	—	2.0	mA	
	I _{CCTA}	V _{IHA} = V _{CCA} - 0.6 V per input	5.0 ± 0.5	3.6	—	500	μA	

AC Characteristics (input: $t_r = t_f = 2.5 \text{ ns}$, $R_L = 500 \Omega$)

$V_{CCA} = 3.3 \pm 0.3 \text{ V}$

Characteristics	Symbol	Test Condition	CL (pF)	V_{CCB} (V)	Ta = -40 to 85°C		Unit
					Min	Max	
Propagation delay time (Bn → An)	t_{pLH} t_{pHL}	Input: Bn Output: An (DIR = "L")	50	5.0 ± 0.5	1.0	6.8	ns
3-state output enable time (\overline{OE} → An)	t_{pZL} t_{pZH}		50	5.0 ± 0.5	1.0	10.0	
3-state output disable time (\overline{OE} → An)	t_{pLZ} t_{pHZ}		50	5.0 ± 0.5	1.0	9.5	
Propagation delay time (An → Bn)	t_{pLH} t_{pHL}	Input: An Output: Bn (DIR = "H")	50	5.0 ± 0.5	1.0	6.8	ns
3-state output enable time (\overline{OE} → Bn)	t_{pZL} t_{pZH}		50	5.0 ± 0.5	1.0	10.0	
3-state output disable time (\overline{OE} → Bn)	t_{pLZ} t_{pHZ}		50	5.0 ± 0.5	1.0	9.5	
Output to output skew	t_{osLH} t_{osHL}	(Note 12)	50	5.0 ± 0.5	—	1.0	ns

Note 12: Parameter guaranteed by design.

$$(t_{osLH} = |t_{pLHm} - t_{pLHn}|, t_{osHL} = |t_{pHLm} - t_{pHLn}|)$$

$V_{CCA} = 2.5 \pm 0.2 \text{ V}$

Characteristics	Symbol	Test Condition	CL (pF)	V_{CCB} (V)	Ta = -40 to 85°C		Unit
					Min	Max	
Propagation delay time (Bn → An)	t_{pLH} t_{pHL}	Input: Bn Output: An (DIR = "L")	30	5.0 ± 0.5	1.0	9.0	ns
3-state output enable time (\overline{OE} → An)	t_{pZL} t_{pZH}		30	5.0 ± 0.5	1.0	12.5	
3-state output disable time (\overline{OE} → An)	t_{pLZ} t_{pHZ}		30	5.0 ± 0.5	1.0	11.5	
Propagation delay time (An → Bn)	t_{pLH} t_{pHL}	Input: An Output: Bn (DIR = "H")	50	5.0 ± 0.5	1.0	10.0	ns
3-state output enable time (\overline{OE} → Bn)	t_{pZL} t_{pZH}		50	5.0 ± 0.5	1.0	12.5	
3-state output disable time (\overline{OE} → Bn)	t_{pLZ} t_{pHZ}		50	5.0 ± 0.5	1.0	11.5	
Output to output skew	t_{osLH} t_{osHL}	(Note 12)	30 or 50	5.0 ± 0.5	—	1.0	ns

Note 12: Parameter guaranteed by design.

$$(t_{osLH} = |t_{pLHm} - t_{pLHn}|, t_{osHL} = |t_{pHLm} - t_{pHLn}|)$$

Capacitive Characteristics (Ta = 25°C)

V_{CCB} = 5.0 V

Characteristics	Symbol	Test Circuit	Test Condition	V _{CCA} (V)	Typ.	Unit
Input capacitance	C _{IN}	—	DIR, $\overline{\text{OE}}$	2.5, 3.3	7	pF
Output capacitance	C _{I/O}	—	An, Bn	2.5, 3.3	8	pF
Power dissipation capacitance (Note 13)	C _{PDA}	—	A ⇒ B (DIR = "H")	2.5, 3.3	2	pF
			B ⇒ A (DIR = "L")	2.5, 3.3	26	
	C _{PDB}	—	A ⇒ B (DIR = "H")	2.5, 3.3	36	pF
			B ⇒ A (DIR = "L")	2.5, 3.3	4	

Note 13: C_{PD} is defined as the value of the internal equivalent capacitance which is calculated from the operating current consumption without load.




Average operating current can be obtained by the equation:

$$I_{CC(\text{opr})} = C_{PD} \cdot V_{CC} \cdot f_{IN} + I_{CC}/16 \text{ (per bit)}$$

Package Dimensions

TSSOP48-P-0061-0.50

Unit : mm



Weight: 0.25 g (typ.)

RESTRICTIONS ON PRODUCT USE

000707EBA

- TOSHIBA is continually working to improve the quality and reliability of its products. Nevertheless, semiconductor devices in general can malfunction or fail due to their inherent electrical sensitivity and vulnerability to physical stress. It is the responsibility of the buyer, when utilizing TOSHIBA products, to comply with the standards of safety in making a safe design for the entire system, and to avoid situations in which a malfunction or failure of such TOSHIBA products could cause loss of human life, bodily injury or damage to property.
In developing your designs, please ensure that TOSHIBA products are used within specified operating ranges as set forth in the most recent TOSHIBA products specifications. Also, please keep in mind the precautions and conditions set forth in the "Handling Guide for Semiconductor Devices," or "TOSHIBA Semiconductor Reliability Handbook" etc..
- The TOSHIBA products listed in this document are intended for usage in general electronics applications (computer, personal equipment, office equipment, measuring equipment, industrial robotics, domestic appliances, etc.). These TOSHIBA products are neither intended nor warranted for usage in equipment that requires extraordinarily high quality and/or reliability or a malfunction or failure of which may cause loss of human life or bodily injury ("Unintended Usage"). Unintended Usage include atomic energy control instruments, airplane or spaceship instruments, transportation instruments, traffic signal instruments, combustion control instruments, medical instruments, all types of safety devices, etc.. Unintended Usage of TOSHIBA products listed in this document shall be made at the customer's own risk.
- The products described in this document are subject to the foreign exchange and foreign trade laws.
- The information contained herein is presented only as a guide for the applications of our products. No responsibility is assumed by TOSHIBA CORPORATION for any infringements of intellectual property or other rights of the third parties which may result from its use. No license is granted by implication or otherwise under any intellectual property or other rights of TOSHIBA CORPORATION or others.
- The information contained herein is subject to change without notice.