



Silicon Switching Diode Array

- For high-speed switching applications
- Connected in series
- Internal (galvanic) isolated diodes in one package



Type	Marking	Pin Configuration						Package
BAV 99U	A7s	1=A1	2=C2	3=C1/A2	4=A1	5=C2	6=C1/A2	SC-74

Maximum Ratings

Parameter	Symbol	Value	Unit
Diode reverse voltage	V_R	70	V
Peak reverse voltage	V_{RM}	70	
Forward current	I_F	200	mA
Surge forward current, $t = 1 \mu s$	I_{FS}	4.5	A
Total power dissipation, $T_S = 113^\circ C$	P_{tot}	250	mW
Junction temperature	T_j	150	$^\circ C$
Storage temperature	T_{stg}	-65 ... 150	

Thermal Resistance


Junction - ambient 1)	R_{thJA}	≤ 420	K/W
Junction - soldering point	R_{thJS}	≤ 150	K/W

1) Package mounted on epoxy pcb 40mm x 40mm x 1.5mm / 0.5cm² Cu

Electrical Characteristics at $T_A = 25^\circ\text{C}$, unless otherwise specified.

Parameter	Symbol	Values			Unit
		min.	typ.	max.	
DC characteristics					
Breakdown voltage $I_{(\text{BR})} = 100 \mu\text{A}$	$V_{(\text{BR})}$	70	-	-	V
Forward voltage $I_F = 1 \text{ mA}$ $I_F = 10 \text{ mA}$ $I_F = 50 \text{ mA}$ $I_F = 150 \text{ mA}$	V_F	-	-	715 855 1000 1250	mV
Reverse current $V_R = 70 \text{ V}$	I_R	-	-	2.5	μA
Reverse current $V_R = 25 \text{ V}, T_A = 150^\circ\text{C}$ $V_R = 70 \text{ V}, T_A = 150^\circ\text{C}$	I_R	-	-	30 50	
AC characteristics					
Diode capacitance $V_R = 0 \text{ V}, f = 1 \text{ MHz}$	C_D	-	-	1.5	pF
Reverse recovery time $I_F = 10 \text{ mA}, I_R = 10 \text{ mA}, R_L = 100 \Omega$, measured at $I_R = 1 \text{ mA}$	t_{rr}	-	-	6	ns

Test circuit for reverse recovery time




Pulse generator: $t_p = 100\text{ns}$, $D = 0.05$,
 $t_r = 0.6\text{ns}$, $R_i = 50\Omega$


Oscilloscope: $R = 50\Omega$, $t_r = 0.35\text{ns}$,
 $C \leq 1\text{pF}$

Forward current $I_F = f(T_A^*; T_S)$

* Package mounted on epoxy




Permissible Pulse Load $R_{thJS} = f(t_p)$




Forward current $I_F = f(V_F)$

$T_A = 25^\circ\text{C}$




Permissible Pulse Load

$I_{Fmax} / I_{FDC} = f(t_p)$



Forward voltage $V_F = f(T_A)$



Reverse current $I_R = f(T_A)$

