

B-XLM-W5 Series

0.5W, FIXED INPUT, ISOLATED&UNREGULATED SINGLE OUTPUT, SUPERMINIATURE SIP6 PACKAGE



FEATURES

- ◆RoHS compliant
- ◆Efficiency up to 80%
- ◆Miniature SIP Package Style
- ♦Wide temperature performance at full 0.5

Watt load,-40°C to 85 °C

- ◆UL 94V-0 package material
- ◆No heat sink required
- Industry standard pin out
- ◆Power sharing on output
- ◆1KVDC isolation
- ◆Continuous Short Circuit Protection
- ◆Internal SMD construction
- ◆No external components required

MODEL SELECTION B 05 05 05 LM -W5

①Product Series

3 Output Voltage

3 Output Voltage 5 Package Style

2 Input Voltage

4)Fixed Input

6Rated Power

APPLICATIONS

The B_XLM-W5 Series are specially designed for applications where a group of polar power supplies are isolated from the input power supply in a distributed power supply system on a circuit board.

These products apply to:

- 1) Where the voltage of the input power supply is fixed (voltage variation ≤ ±10%);
- 2) Where isolation is necessary between input and output (isolation voltage ≤1000VDC);
- 3) Where the regulation of the output voltage and the output ripple noise are not demanding.

Such as:purely digital circuits, ordinary low frequency analog circuits, and IGBT power device driving circuits.





SELECTION GUIDE							
Order code*	Input		Output			Efficiency	Switching
	Voltag Nominal	e(VDC) Range	Voltage (VDC)	Cui	rent Min	(%,Typ)	Frequency (KHz,Typ)
B0505XLM-W25	5	4.5-5.5.	5	50	5	79	83
B0505XLM-W5	5	4.5-5.5	5	100	10	70	82
B0509XLM-W5	5	4.5-5.5	9	56	6	75	83
B0512XLM-W5	5	4.5-5.5	12	42	4	79	83
B0515XLM-W5	5	4.5-5.5	15	33	3	80	80
B0524XLM-W5	5	4.5-5.5	24	21	2	78	84
B1205XLM-W5	12	10.8-13	5	100	10	72	84
B1209XLM-W5	12	10.8-13	9	56	6	75	81
B1212XLM-W5	12	10.8-13	12	42	4	77	82
B1215XLM-W5	12	10.8-13	15	33	3	79	83
B1224XLM-W5	12	10.8-13	24	21	2	81	84
B2405XLM-W5	24	21.6-26	5	100	10	70	82
B2409XLM-W5	24	21.6-26	9	56	6	73	83
B2412XLM-W5	24	21.6-26	12	42	4	75	83
B2415XLM-W5	24	21.6-26	15	33	3	78	80
B2424XLM-W5	24	21.6-26	24	21	2	77	84

^{*} add Suffix "P" for Continuous Short Circuit Protection, e.g. B0505XLM-W5P

ISOLATION SPECIFICATIONS						
Parameter	Test conditions	Min.	Тур.	Max.	Units	
Isolation test voltage	Flash tested for 1 minute and 1mA max	1000			VDC	
Isolation resistance	Test at Viso=500VDC	1000			ΜΩ	

OUTPUT SPECIFICATIONS					
Test conditions	Min.	Тур.	Max	Unit	
	0.05		0.5	w	
For Vin change of 1%			1.2		
10% to 100% full load(5V output)		10	15	- %	
10% to 100% full load(9V output)		8.3	10		
10% to 100% full load(12V output)		6.8	10		
10% to 100% full load(15V output)		6.3	10		
10% to 100% full load(24V output)		5	10		
	See	See tolerance envelope graph		raph	
100% full load		0.03 %		%/°C	
20MHz Bandwidth(B-XLM-W5)		75	100	MV p-p	
100% load, nominal input(5V,12V)		100		- Khz	
100% load, nominal input(24V)		500			
	Test conditions For Vin change of 1% 10% to 100% full load(5V output) 10% to 100% full load(9V output) 10% to 100% full load(12V output) 10% to 100% full load(15V output) 10% to 100% full load(24V output) 10% to 100% full load(24V output) 100% full load 20MHz Bandwidth(B-XLM-W5) 100% load, nominal input(5V,12V)	Test conditions 0.05 For Vin change of 1% 10% to 100% full load(5V output) 10% to 100% full load(9V output) 10% to 100% full load(12V output) 10% to 100% full load(15V output) 10% to 100% full load(24V output) See 100% full load 20MHz Bandwidth(B-XLM-W5) 100% load, nominal input(5V,12V)	Test conditions Min. Typ. 0.05 0.05 For Vin change of 1% 10% to 100% full load(5V output) 10 10% to 100% full load(9V output) 8.3 10% to 100% full load(12V output) 6.8 10% to 100% full load(15V output) 6.3 10% to 100% full load(24V output) 5 See tolerance 100% full load 0. 20MHz Bandwidth(B-XLM-W5) 75 100% load, nominal input(5V,12V) 100	Test conditions Min. Typ. Max 0.05 0.5 For Vin change of 1% 1.2 10% to 100% full load(5V output) 10 15 10% to 100% full load(9V output) 8.3 10 10% to 100% full load(12V output) 6.8 10 10% to 100% full load(15V output) 6.3 10 10% to 100% full load(24V output) 5 10 See tolerance envelope g 100% full load 0.03 20MHz Bandwidth(B-XLM-W5) 75 100 100% load, nominal input(5V,12V) 100	


^{*} Test ripple and noise by "parallel cable" method. See detailed operation instructions at Testing of Power Converter section, application notes.




COMMON SPECIFICATIONS Parameter Тур. Max Storage humidity range 95 -40 85 Operating temperature -55 125 Storage temperature $^{\circ}\!\mathbb{C}$ Lead temperature 1.5mm from case for 10 seconds 300 Temp.rise at full load 15 25 Cooling Free air convection Case material Plastic(UL94-V0) Continuous Short circuit protection 3500 MTBF K hours Weight

TYPICAL CHARACTERISTICS Temperature Derating Graph Temperature Derating Graph Tolerance Envelope Graph 120 +10% Typical Load Line.... 100 Output Power(%) +2.5% Nominal 80 -2.5% Voltage 60 Voltage -7.5% Safe Operating Area 40 50% 10% 100% Output Current (%) Operating Temp.(°C)

OUTLINE DIMENSIONS & PIN CONNECTIONS





Unit:mm(inch) Pin section:0.50*0.3mm(0.020*0.012inch) Pin section tolerances:±0.10mm(±0.004inch) General tolerances: ±0.25mm(±0.010inch)

RECOMMENDED FOOTPRINT Top view,grid:2.54mm(0.1inch) eter:1.00mm(0.039inch) Single Ф Ф 2 4 1 6

POOTPRINT DETAILS				
Pin	Single			
1	VIN			
2	GND			
4	0V			
5	NC			
6	+Vo			

N C - Not available for electrical connection

Requirement on output load

To ensure this module can operate efficiently and reliably, a minimum load is specified for this kind of DC/DC converter in addition to a maximum load(namely full load). During operation, make sure the specified range of input voltage is not exceeded, the minimum output load is not less than 10% of the full load, and that this product should **never be operated under no load!**


B-XLM-W5 Series

Overload Protection

Under normal operating conditions, the output circuit of these products has no protection against overload. The simplest method is to connect a self-recovery fuse in series at the input end or add a circuit breaker to the circuit.

mended testing and application circuit

If you want to further decrease the input/output ripple, an "LC" filtering network may be connected to the input and output ends of the DC/DC converter, see



It should also be noted that the inductance and the frequency of the "LC" filtering network should be staggered with the DC/DC frequency to avoid $\,$ mutual interference. However, the capacitance of the output filter capacitor must be proper. If the capacitance is too big, a startup problem might arise. For every channel of output, provided the safe and reliable operation is ensured, the greatest capacitance of its filter capacitor sees (Table 1).


EXTERNAL CAPACITOR TABLE (TABLE 1)

Vin	Cin	Vout	Cout
(VDC)	(µF)	(VDC)	(µF)
5	47	5	10
12	2.2	9	4.7
24	1.0	12	2.2
		15	1

It's not recommend to connect any external capacitor in the application field with less than 0.5 watt output.

Output Voltage Regulation and Over-voltage Protection Circuit

The simplest device for output voltage regulation, over-voltage and over-current protection is a linear voltage regulator with overheat that is connected to the input or output end in series (Figure 2).



When the environment temperature is higher than 71°C, the product output power should be less than 60% of the rated power.

No parallel connection or plug and play.



Microdc Professional Power Module,Inc.

Tel:0086-20-86000646 E-mail:tech@microdc.cn Website:http://www.microdc.cn



ROHS COMPLIANT INFORMATION

This series is compatible with RoHS soldering systems with a peak wave solder temperature of 300° C for 10 seconds. The pin termination finish on the SIP package type is Tin Plate, Hot Dipped over Matte Tin with Nickel Preplate. The DIP types are Matte Tin over Nickel Preplate. Both types in this series are backward compatible with Sn/Pb soldering



REACH COMPLIANT INFORMATION

This series has proven that this product does not contain harmful chemicals, it also has harmful chemical substances through the registration, inspection and approval.

^{*}Supply voltage must be discontinued at the end of short circuit duration.