

VOLTAGE REGULATORS

NEGATIVE, 3 TERMINAL, ARRANGED BY OUTPUT VOLTAGE

Regulated Voltage Out $\pm 5\%$ (Volts)	NTE Type Number	Case Style	Diagram Number	Voltage In (Volts)		Output Current (Amps)	Power Dissipation (Watts)
V_{out}				V_{in}			
				Min	Max		
-5V	961	TO220	11g	-7	-35	1	15
-5V	1913	TO3	1e	-7.1	-35	1.5	15
-5V	1917	TO92	9p	-7.3	-35	0.1	0.7
-6V	963	TO220	11g	-8	-35	1	15
-8V	965	TO220	11g	-10.5	-35	1	15
-12V	967	TO220	11g	-14.5	-35	1	15
-12V	1903	TO92	9q	-13.7	-35	0.1	0.7
-12V	1915	TO3	1e	-14.1	-35	1.5	15
-15V	969	TO220	11g	-17.5	-35	1	15
-15V	1905	TO92	9p	-16.7	-35	0.1	0.7
-15V	1919	TO3	1e	-17.1	-40	1.5	15
-18V	959	TO220	11g	-21	-35	1	15
-18V	1907	TO92	9q	-19.7	-35	0.1	0.7
-18V	1923	TO3	1e	-20.1	-40	1.5	15
-24V	971	TO220	11g	-27	-40	1	15
-24V	1909	TO92	9p	-27	-40	0.1	0.7
-24V	1925	TO3	1e	-26.1	-40	1.5	15

NEGATIVE ADJUSTABLE, ARRANGED BY OUTPUT VOLTAGE

Adjustable Range of Regulated Voltage Output (Volts)	NTE Type Number	Case Style	Diagram Number	Voltage In (Volts)		Output Current (Amps)	Power Dissipation (Watts)
V _{out}				V _{in}		I _o	P _D
				Min	Max		
-2.2V to -30V	954	4-Lead Power Tab	308b	-7.5	-40	1	15
-2.2V to -30V	1927	4-Lead TO3	414b	-7.5	-40	1	15
-1.2V to -37V	957	TO220	11i	-3	-40	1.5	15
-1.2V to -37V	1901	TO92	9q	-3	-40	0.1	0.625
-1.2V to -37V	1911	TO3	1d	-3	-40	1.5	20

PRECISION VOLTAGE REGULATORS

(0.01% LINE AND LOAD REGULATION)

POSITIVE OR NEGATIVE SUPPLY

Adjustable Range of Regulated Voltage Output (Volts)	NTE Type Number	Case Style	.Diagram Number	Voltage In (Volts)		Output Current (Amps)	Power Dissipation (Watts)
V _{out}				V _{in}			
				Min	Max	I _o	P _D
±2V to ±37V	923	10-Lead Metal Can	201	9.5	40	0.15	0.8
±2V to ±37V	923D	14-Lead DIP	247	9.5	40	0.15	1