


Flachstecker
mit Steckerbreite 6,3 mm
zum Einrasten in Gehäuse



Tabs
with tab width 6.3 mm
to engage in housings

Typ 1



Typ	Nenn- quer- schnitt qmm	Steck- dicke	Steck- breite	a1	a2	d2	h	L1	L2	L4	Mat- dicke	Form E=Einzel B=Band	Teile-Nr.	Werkstoff	Oberfläche	Verb.- vor- schub	Fuß- note
1	0,5 - 1 (0,3)	0,80	6,30	8,20	4,00	1,65	1,40	28,00	16,00	15,50	0,37	B	25068.213.009	CuSn		L	
1	0,5 - 1	0,80	6,30	8,20	4,00	1,65	1,80	28,00	16,00	15,50	0,38	B	25297.123.009	CuZn		SQ	
												B	25297.123.041	CuZn	Ag 1		
												B	25297.123.043	CuZn	Ag 5		
												B	25297.123.113	CuZn	Sn 8		
												B	25297.123.178	CuZn	frSn 2		
												B	25297.213.009	CuSn			
												B	25297.213.041	CuSn	Ag 1		
												B	25297.213.111	CuSn	Sn 3		
												E	05297.123.009	CuZn			
												E	05297.123.041	CuZn	Ag 1		
												E	05297.123.178	CuZn	frSn 2		
												E	05297.213.009	CuSn			
												E	05297.213.111	CuSn	Sn 3		
												E	45297.123.178	CuZn	frSn 2		
												E	45297.213.041	CuSn	Ag 1		
1	0,5 - 1	0,80	6,30	8,20	4,00		1,80	28,00	16,00	15,50	0,38	B	25448.123.111	CuZn	Sn 3	SQ	*1
												B	25448.213.009	CuSn			*1
												B	25448.213.011	CuSn	Sn 3		*1
												E	05448.123.011	CuZn	Sn 3		*1
												E	05448.213.011	CuSn	Sn 3		*1
1	über 1 - 2,5	0,80	6,30	8,20	4,00	1,65	1,80	28,00	16,00	15,50	0,38	B	25054.123.009	CuZn		SQ	
												B	25054.123.041	CuZn	Ag 1		
												B	25054.123.042	CuZn	Ag 3		
												B	25054.123.043	CuZn	Ag 5		
												B	25054.123.113	CuZn	Sn 8		
												B	25054.123.178	CuZn	frSn 2		
												B	25054.213.009	CuSn			
												B	25054.213.041	CuSn	Ag 1		
												B	25054.213.042	CuSn	Ag 3		
												B	25054.213.111	CuSn	Sn 3		
												E	05054.123.009	CuZn			
												E	05054.123.041	CuZn	Ag 1		
												E	05054.123.178	CuZn	frSn 2		
												E	05054.213.009	CuSn			
												E	05054.213.042	CuSn	Ag 3		
												E	05054.213.111	CuSn	Sn 3		
												E	45054.123.009	CuZn			
												E	45054.123.041	CuZn	Ag 1		
												E	45054.123.178	CuZn	frSn 2		
												E	45054.213.111	CuSn	Sn 3		
												E	45054.213.142	CuSn	Ag 3		
1	über 1 - 2,5	0,80	6,30	8,20	4,00		1,80	28,00	16,00	15,50	0,38	B	25447.123.009	CuZn		SQ	*1
												B	25447.123.041	CuZn	Ag 1		*1
												B	25447.123.042	CuZn	Ag 3		*1
												B	25447.123.098	CuZn	Ni 2 Ag 3		*1
												B	25447.213.009	CuSn			*1
												B	25447.213.041	CuSn	Ag 1		*1
												E	05447.123.009	CuZn			*1
												E	05447.123.041	CuZn	Ag 1		*1
												E	05447.123.042	CuZn	Ag 3		*1
												E	05447.123.078	CuZn	Ni 3 Ag 5		*1
												E	05447.123.111	CuZn	Sn 3		*1
												E	05447.213.042	CuSn	Ag 3		*1
												E	45447.213.011	CuSn	Sn 3		*1
*1 Steckzunge ohne Rastloch																	
*1 Tab without locking hole																	

16130,001