



WR - 90 Seamless Flexible Waveguide, UG - 39 / U S
Cover Flange Operating From 8.2 GHz to 12.4 GHz

Flexible Waveguides Technical Data Sheet

PE-W90SF005-24

Features

- WR-90 waveguide
- Flexes in both the E and H plane
- 8.2 GHz to 12.4 GHz Frequency Range
- Brass flanges with a silver plating
- Neoprene sleeve provides added protection and mechanical support

Applications

- Allows expansion/contraction due to thermal issues.
- Test Benches
- Microwave Radio
- Eliminates installation problems caused by misalignment.
- Pressurized waveguide systems
- Provides vibration isolation

Description

The PE - W90SF005 - 24 is part of Pasternack's family of flexible waveguides. The waveguide body is made of silver plated brass. It can be bent in both the E and H planes without impairing VSWR or attenuation. The waveguide is covered by a neoprene jacket which protects the waveguide and provides mechanical support.

Electrical Specifications

Description	Minimum	Typical	Maximum	Units
Frequency Range	8.2		12.4	GHz
VSWR		1.07:1		
Insertion Loss		0.18		dB

Mechanical Specifications

Waveguide Size	WR-90
Waveguide Design	Seamless
Section Length	24 [in [609.6 mm]]
E - Plane Minimum Bend Radius	0087 [in] 22.1 mm
H - Plane Minimum Bend Radius	1060 [in] 42.93 mm
Maximum Operating Pressure	45 psig

Description	Flange 1	Waveguide	Flange 2
Type	Square Cover	WR-90	Square Cover
Designation	UG - 39 / U		UG - 39 / U
Material	Brass	Brass	Brass
Plating		Silver	
Color	Gold	Black	Gold


Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and more: [WR-90 Seamless Flexible Waveguide, UG-39 / 8.2 GHz to 12.4 GHz PE-W90SF005-24](#)



WR - 90 Seamless Flexible Waveguide, UG - 39 / U Square Cover Flange Operating From 8.2 GHz to 12.4 GHz

Flexible Waveguides Technical Data Sheet

PE-W90SF005-24



WR - 90 Seamless Flexible Waveguide, UG - 39 / U Square Cover Flange
Pasternack Enterprises has same day shipment for worldwide and wave products maintain a 99% availability and are part of the broadest selection in the industry.

Click the following link (or enter part number in "SEARCH" inventory and [WR - 90 Seamless Flexible Waveguide, UG - 39 / U Square Cover Flange Operating From 8.2 GHz to 12.4 GHz PE-W90SF005-24](https://www.pasternack.com/wr90-seamless-flexible-waveguide-ug-39-u-square-cover-flange-operating-from-8.2-ghz-to-12.4-ghz-pe-w90sf005-24)

URL: <https://www.pasternack.com/wr90-seamless-flexible-waveguide-ug-39-u-square-cover-flange-operating-from-8.2-ghz-to-12.4-ghz-pe-w90sf005-24>


The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order to implement improvements. Pasternack reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. Pasternack does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and Pasternack does not assume any liability arising out of the use of any part or documentation.

PE-W90SF005-24 CAD Drawing

WR - 90 Seamless Flexible Waveguide, UG - 39/U
 Flange Operating From 8.2 GHz to 12.4



PASTERNAK
 PE-W90SF005-24



NOTES:
 1. UNLESS OTHERWISE SPECIFIED ALL DIMENSIONS ARE NOMINAL.
 2. ALL SPECIFICATIONS ARE SUBJECT TO CHANGE WITHOUT NOTICE AT ANY TIME.
 3. DIMENSIONS ARE IN INCHES [mm].

DWG TITLE
PE-W90SF005-24

(PE) PASTERNAK
 THE ENGINEER'S RF SOURCE
 Pasternack Enterprises, Inc.
 P.O. Box 16759 | Irvine | CA | 92623
 Phone: (949) 261-1920 | Fax: (949) 261-7451
 Website: www.pasternack.com | E-Mail: sales@pasternack.com

FSCM NO. 53919	CAD FILE 101315	SCALE N/A	SIZE A	2233
----------------	-----------------	-----------	--------	------