

NPN DIGITAL TRANSISTOR (BUILT-IN RESISTORS)

FEATURES

- * Built-in bias resistors enable the configuration of an inverter circuit without connecting external input resistors (see equivalent circuit).
- * The bias resistors consist of thin-film resistors with complete isolation to allow negative biasing of the input. They also have the advantage of almost completely eliminating parasitic effects.
- * Only the on/off conditions need to be set for operation, making device design easy.



EQUIVALENT CIRCUIT





MARKING

ABSOLUTE MAXIMUM RATINGS (Ta = 25°C)

PARAMETER	SYMBOL	RATINGS	UNIT
Supply voltage	Vcc	50	V
Input voltage	Vin	-5 ~ + 12	V
Output current	lo	100	A
	IC (Max.)	100	mA
Power Dissipation	PD	200	mW
Junction temperature	Tj	150	$^{\circ}$
Storage temperature	Tstg	-55 ~ +150	$^{\circ}$

ELECTRICAL CHARACTERISTICS (Ta = 25°C)


SYMBOL	TEST CONDITIONS	MIN	TYP	MAX	UNIT
VI (off)	Vcc=5V, Io=100 μ A			0.5	V
VI (on)	Vo=0.3V, Io=5mA	1.1			V
Vo (on)	Io/Ii=5mA/0.25mA		0.1	0.3	V
lı	Vi=5V			3.6	mA
IO (off)	Vcc=50V, Vi=0V			0.5	μA
Gı	Vo=5V, Io=10mA	80			
R1		1.54	2.2	2.86	ΚΩ
R2/R1		17	21	26	
fτ	VcE=10V, IE=-5mA, f=100MHz *		250		MHz
	VI (off) VI (on) VO (on) II IO (off) GI R1 R2/R1	V _I (off) Vcc=5V, lo=100 μ A V _I (on) Vo=0.3V, lo=5mA Vo (on) lo/li=5mA/0.25mA II Vi=5V lo (off) Vcc=50V, Vi=0V GI Vo=5V, lo=10mA R1 R2/R1	VI (off) Vcc=5V, Io=100 μ A VI (on) Vo=0.3V, Io=5mA VO (on) Io/Ii=5mA/0.25mA II Vi=5V Io (off) Vcc=50V, Vi=0V GI Vo=5V, Io=10mA 80 R1 1.54 R2/R1 17 fT Vce=10V, Ie=-5mA, f=100MHz *	VI (off) Vcc=5V, Io=100 μA VI (on) Vo=0.3V, Io=5mA VO (on) Io/Ii=5mA/0.25mA II Vi=5V Io (off) Vcc=50V, Vi=0V GI Vo=5V, Io=10mA R1 1.54 R2/R1 17 21 Tr TT VcE=10V, IE=-5mA, f=100MHz	VI (off) Vcc=5V, Io=100 μ A 0.5 VI (on) Vo=0.3V, Io=5mA 1.1 Vo (on) Io/Ii=5mA/0.25mA 0.1 0.3 II Vi=5V 3.6 Io (off) Vcc=50V, Vi=0V 0.5 GI Vo=5V, Io=10mA 80 R1 1.54 2.2 2.86 R2/R1 17 21 26 fT Vce=10V, Ie=-5mA, f=100MHz * 250


* Transition frequency of the device




UNISONIC TECHNOLOGIES CO. LTD


ELECTRICAL CHARACTERISTIC CURVES





OUTPUT CURRENT, Io (A)





UTC assumes no responsibility for equipment failures that result from using products at values that exceed, even momentarily, rated values (such as maximum ratings, operating condition ranges, or other parameters) listed in products specifications of any and all UTC products described or contained herein. UTC products are not designed for use in life support appliances, devices or systems where malfunction of these products can be reasonably expected to result in personal injury. Reproduction in whole or in part is prohibited without the prior written consent of the copyright owner. The information presented in this document does not form part of any quotation or contract, is believed to be accurate and reliable and may be changed without notice.

LITC

UNISONIC TECHNOLOGIES CO. LTD

2