
MBR10100C


SCHOTTKY BARRIER RECTIFIER

■ FEATURES

- * 10 amps total (5 amps per diode leg)
- * Guard ring for transient protection
- * Low forward voltage drop
- * High surge capability
- * Low power loss/High efficiency

■ SYMBOL






*Pb-free plating product number: MBR10100CL

ORDERING INFORMATION

| Order Number | | Dookogo | Pin Assignment | | | Dooking |
|-----------------|-------------------|---------|----------------|---|---|---------|
| Normal | Lead Free Plating | Package | 1 | 2 | 3 | Packing |
| MBR10100C-TA3-T | MBR10100CL-TA3-T | TO-220 | Α | K | Α | Tube |

Note: Pin Assignment: A: Anode K: Cathode



www.unisonic.com.tw 1 of 1

MBR10100C DIODE

■ ELECTRICAL CHARACTERISTICS (Ta=25 , unless otherwise specified)

| PARAMETER | SYMBOL | RATINGS | UNIT | |
|--|--|--------------------|------|---|
| Maximum Repetitive Peak Reverse Volta | V_{RRM} | 100 | V | |
| Maximum non-repetitive Peak Reverse | V_{RM} | 100 | V | |
| Maximum DC Blocking Voltage | V_R | 100 | V | |
| Average Forward Rectified Output | Per Leg | | 5 | Α |
| Current | Total Device | lout | 10 | Α |
| Famurand Voltage | I _F =5A, T _C =25 | | 0.85 | V |
| Forward Voltage | $I_F=10A, T_C=25$ | V _F | 0.95 | V |
| Maximum DC Reverse Current@ V _R =10 | I_R | 0.1 | mA | |
| Junction Capacitance (Note 1) | CJ | 300 | pF | |
| Operating Temperature | TJ | -55 ~ + 150 | | |
| Storage Temperature | T _{STG} | -55 ~ + 150 | | |

Note.1: Applied $V_R = 4.0V$ and f = 1.0MHz.

UTC assumes no responsibility for equipment failures that result from using products at values that exceed, even momentarily, rated values (such as maximum ratings, operating condition ranges, or other parameters) listed in products specifications of any and all UTC products described or contained herein. UTC products are not designed for use in life support appliances, devices or systems where malfunction of these products can be reasonably expected to result in personal injury. Reproduction in whole or in part is prohibited without the prior written consent of the copyright owner. The information presented in this document does not form part of any quotation or contract, is believed to be accurate and reliable and may be changed without notice.