




CS4226

Surround Sound Codec

The following information is based on the
technical datasheet:

CS4226 DS188PP5 NOV '96

Please contact Cirrus Logic : Crystal
Semiconductor Products Division for further
information.

CRYSTAL SEMICONDUCTOR PRODUCTS DIVISION PRODUCT INFORMATION

Copyright © Cirrus Logic, Inc. 1998
(All Rights Reserved)

PI188PP1 JAN '98

Surround Sound Codec


Features

- Stereo 20-bit A/D Converters
- Six 20-bit D/A Converters
- S/PDIF Receiver
 - AC-3® & MPEG Auto-detect Capability
- 108 dB DAC Signal-to-Noise Ratio (EIAJ)
- Mono 20-bit A/D Converter
- Programmable Input Gain & Output Attenuation
- On-chip Anti-aliasing and Output Smoothing Filters
- De-emphasis for 32 kHz, 44.1 kHz, 48 kHz

Description

The CS4226 is a single-chip codec providing stereo analog-to-digital and six digital-to-analog converters using delta-sigma conversion techniques. This +5 V device also contains volume control independently selectable for each of the six D/A channels. An S/PDIF receiver is included as a digital input channel. Applications include Dolby® Pro-logic™, THX®, and Dolby Digital™ AC-3® home theater systems, DSP based car audio systems, and other multi-channel applications.

The CS4226 is packaged in a 44-pin plastic TQFP.



Overview

The CS4226 has 2 channels of 20-bit analog-to-digital conversion and 6 channels of 20-bit digital-to-analog conversion. A mono 20-bit ADC is also provided. All ADCs and DACs are delta-sigma converters. The stereo ADC inputs have adjustable input gain, while the DAC outputs have adjustable output attenuation. The device also contains an S/PDIF receiver capable of receiving compressed AC-3/MPEG or uncompressed digital audio data.

Digital audio data for the DACs and from the ADCs is communicated over separate serial ports. This allows concurrent writing to and reading from the device. Control for the functions available on the CS4226 are communicated over a serial microcontroller interface.

FAQs


- 1) Why does the CS4226 contain an S/PDIF receiver?
A: The CS4226 Surround Sound Codec along with the CS4923 Dolby Digital decoder implements a two chip solution to home theater A/V receivers. The S/PDIF receiver on the CS4226 locks onto the digital audio source (DVD, LD, CD), and transfers the digital audio data to the CS4923 DSP for AC-3 decoding. This CS4226 contains six DACs for playback to six speakers and an A/D converter for digitizing an analog pro-logic source.
- 2) What does the AUTODATA output signal?
A: For AC-3, MPEG, or DTS applications, it is important to know whether the incoming S/PDIF data stream is digital audio or compressed AC-3/MPEG/DTS data. This information is typically conveyed by setting channel status bit 1 (audio/non-audio bit), but some AC-3/MPEG/DTS sources may not strictly adhere to this convention and the bit may not be properly set. The CS4226 S/PDIF receiver can automatically detect the presence of compressed audio data streams by monitoring the sync codes in the data stream. When the sync code is detected, the AUTODATA indicator (pin 10) will go high. The AUTODATA pin can flag the DSP to change algorithms or to mute the DAC outputs.
- 3) Is the CS4226 volume control analog or digital?
A: The CS4226 implements a combined analog/digital volume control architecture which is the optimal solution for performance and cost. The first 24 dB of attenuation is performed in the analog domain which reduces the residual output noise to that achieved in the mute state. Because the attenuation is performed in the analog domain, as the signal is attenuated the noise floor is attenuated thus preserving dynamic range. The remaining attenuation is performed digitally to a maximum attenuation of 86 dB.

- 4) Why is de-emphasis performed in the S/PDIF receiver data path?
- A: The CS4226 S/PDIF receiver acquires data from a digital audio source (i.e. CD, DVD player) and transfers the data to a digital signal processor (DSP). If the data from the digital audio source is pre-emphasized, then de-emphasis should be performed prior to the DSP so that the DSP can process audio data with a flat frequency response.

Ordering Information

CS4226-KQ	TQFP, -10 °C to +70 °C
CDB4226	Evaluation Board

For further information on Crystal products, please visit our website “www.crystal.com” or call our literature department (800) 888-5016 ext. 3594 or (512) 912-3594 for data sheets and application notes.



Sales Office and Applications Support

UNITED STATES

Sales Office and Applications Support:

WESTERN AREA

Cirrus Logic
Crystal Semiconductor Div.
50 Airport Pkwy.
San Jose, CA 95110
Ph: 408-437-7743
FAX: 408-437-4943

Cirrus Logic
Crystal Semiconductor Div.
6 Venture,
Ste. 100
Irvine, CA 92718
Ph: 714-453-5910
FAX: 714-453-5914

CENTRAL AREA

Cirrus Logic
Crystal Semiconductor Div.
14205 Burnet Rd.,
Ste. 400
Austin, TX 78728
Ph: 512-255-8893
FAX: 512-255-0733

EASTERN AREA

Cirrus Logic
Crystal Semiconductor Div.
5511 Capital Center Dr.,
Ste. 103
Raleigh, NC 27606
Ph: 919-859-5393
FAX: 919-859-5334

Cirrus Logic
10 New England Business Center,
Ste. 100
Andover, MA 01810
Ph: 978-794-9138
FAX: 978-794-9998

Cirrus Logic
Crystal Semiconductor Div.
10440 Little Patuxent Pkwy.,
Ste. 300
Columbia, MD 21044-3559
Ph: 410-740-5654
FAX: 410-740-6961

EUROPE

Sales Office and Applications Support:

Cirrus Logic France
Immeuble Andre Malraux
93561 Rosny s/s Bois CEDEX,
France
Ph: +33(148)122812
FAX: +33(148)122810

Cirrus Logic
Crystal Semiconductor (UK) Ltd.
Spectrum Point,
279 Farnborough Rd.,
Farnborough,
Hampshire GU14 7LS,
United Kingdom
Ph: +44(0)1252372762
FAX: +44(0)1252372763

Cirrus Logic GmbH
Muehlfelder-Strasse 2
D-82211 Herrsching, Germany
Ph: +49(08152)92460
FAX: +49(08152)924699

FAR EAST

Sales Office and Applications Support:

CHINA

Cirrus Logic International Ltd.
A-1403, Qiancun Commercial
Mansion
Beijing, China 100029
Ph: (8610)6443-0783
Ph: (8610)6443-0784
Ph: (8610)6443-0785
FAX: (8610)6443-0786

HONG KONG

Cirrus Logic International Ltd.
1203 Park Tower
15 Austin Rd., Tsimshatsui
Kowloon, Hong Kong
Ph: (852)2376-0801
FAX: (852)2375-1202

KOREA

Cirrus Logic, Korea Co., Ltd.
Rm 1302 SangKyung Bldg., 824-
21 YeokSam-Dong,
KangNam-Ku,
Seoul, Korea
Ph: +82(2)565-8561
FAX: +82(2)565-8565

SINGAPORE

Cirrus Logic
Crystal International
6 Kaki Bukit Ave. 1,
Ste. 03-03
Singapore 417940
Ph: +65-743-4111
FAX: +65-742-4111

TAIWAN

Cirrus Logic International Ltd.
Taiwan Branch
10F, No.214 Tun Hwa North Rd.
Taipei, Taiwan R.O.C.
Ph: +886(2)2718-4533
FAX: +886(2)2718-4526

JAPAN

Sales Office and Applications Support:

Cirrus Logic K.K.
Shinjuku Green Tower, Bldg. 26F
6-14-1 Nishi-Shinjuku,
Shinjuku-ku,
Tokyo, 160
Japan
Ph: +81(03)3340-9111
FAX: +81(03)3340-9120



**CRYSTAL SEMICONDUCTOR
PRODUCTS DIVISION**

**PO BOX 17847
4210 S. INDUSTRIAL DRIVE
AUSTIN, TEXAS 78744
512.445.7222 / 800.888.5016
FAX: 512.445.7581**

**WORLDWIDE WEB:
<http://www.crystal.com>**