

13.56MHz RFID Transponder

Features

- Very low operating current (4 μ A @ $V_{DD}=3V$)
- Wide range operating voltage
- Batteryless RF transponder
- Data transmission in read-only operation
- Max. of 64-bits customer programmable data
- 16-bits CRC error detection code
- OTP data memory
- 13.56MHz carrier frequency
- Output data baud rate: 4kbps (Typ.) @ $V_{DD}=3V$
- PWM/ASK modulation
- Built-in voltage limiter

Applications

- Interactive leisure products
- Security system
- Access control
- Anti-counterfeit devices
- Material management
- Animal management
- Personnel working time record
- Car park monitoring system

General Description


The HT6720 is an RF transponder IC with 13.56MHz RF carrier, which provides a low cost batteryless transponder solution when combined with an external inductor. The inductor and internal capacitor form an LC tank which induce voltage from the radiated 13.56MHz carrier signal generated from the reader antenna. HT6720 has a built-in low power RC oscillator which is activated if the induced carrier field strength is high enough to supply the operating current and the response signal (pre-programmed in the OTP memory) is serially transmitted out. The response data is transmitted using PWM/ASK modulation. Modulation of 13.56MHz is accomplished by damping the LC tank with a fixed baud rate.

The transmission information is stored in a 96 bits one time programmable memory OTP, with a 16-bit CRC code (up to 64 bits reserved for customer). The effective detection range for a small sized antenna is 2cm~10cm which is dependent on antenna format & reader design. The larger the antenna loop used the longer the detection range. It is advisable to use larger antenna to attain a 15 cm detection range.


Implementing Holtek's advanced OTP and low power technology, HT6720 offers a very cost effective solution for RF contactless detection system.

A code area of 64-bits (max.) wide is provided so customers can program the device using the specified programmer supplied by Holtek. The pre-programmed ICs are also available upon customer's request.

Block Diagram



Pad Assignment



Chip size: 925×1040 (μm)²

* The IC substrate should be connected to VSS in the PCB layout artwork.

Pad Coordinates

Unit: μm

Pad No.	X	Y	Pad No.	X	Y
1	-256.65	357.34	4	228.70	-361.37
2	-256.65	-361.99	5	219.80	338.59
3	96.10	-378.15	6	88.89	332.15

Pad Description

Pad No.	Pad Name	I/O	Internal Connection	Description
1	HF2	I/O	CMOS	Connect to an antenna coil for normal operation. Open for data programming.
2	HF1	I/O	CMOS	Connect to an antenna coil for normal operation. Data I/O for programming.
3	VSS	—	—	Negative power supply, ground
4	CLK	I	CMOS	Open for normal operation. Clock input for programming.
5	VPA	I	—	Open for normal operation. High voltage supplies input for programming.
6	VDD	—	—	Open for normal operation, +5V supply input for programming.

Absolute Maximum Ratings

Supply Voltage (VDD)6V	Storage Temperature-50°C to 125°C
Supply Voltage (VPA)13.5V	Operating Temperature0°C to 70°C
Input VoltageV _{SS} -0.3V to V _{DD} +0.3V	

Note: These are stress ratings only. Stresses exceeding the range specified under "Absolute Maximum Ratings" may cause substantial damage to the device. Functional operation of this device at other conditions beyond those listed in the specification is not implied and prolonged exposure to extreme conditions may affect device reliability.

Electrical Characteristics

Symbol	Parameter	Test Conditions		Min.	Typ.	Max.	Unit
		V _{DD}	Conditions				
V _{DD}	Operating Voltage	—	V _{DD} pad voltage	2.4	—	5	V
I _{dd}	Operating Current	3V	—	—	4	—	μA
		5V	Voltage limiter not started	—	10	—	μA
R _m	Modulation Resistance	5V	—	—	320	—	Ω
V _{LCL}	LC Input Limiter Voltage	—	—	—	6.5	—	V
B _R	Output Data Baud Rate	3V	V _{DD} vs V _{SS}	—	4	—	Kbps
		5V	V _{DD} vs V _{SS}	—	5.5	—	Kbps

Functional Description


Operation Concept

The reader transmits a 13.56MHz carrier signal from its antenna, the LC tank on the transponder side converts the carrier energy to voltage form and supply to the transponder chip with an internal pump circuit. If the induced energy is high enough, the pumped voltage reaches the break-in voltage of the internal RC-oscillator, the transponder is actuated to transmit its internal data serially by means of damping the LC tank.


The reader receives the transponder's data by means of detecting the energy variation on its own antenna, and recognize the information with a microcontroller.

The HT6720 has a built-in internal Voltage Limiter to prevent excess power supply and RF levels induced by the LC tank from damaging the device or causing the device to function abnormally.

A total of 96 bits of OTP memory space is provided, from which 64 bits wide are customer programmable, which can be programmed using the specified programmer supplied by Holtek. The pre-programmed ICs are also available upon customer's request.



Timing & Code Package



Code Package

A total of 96 bits information can be stored in the HT6720, from which 64 bits are customer programmable.

Agent ID: This 8-bit wide code is not customer programmable and is supplied together with the data writer after registering to Holtek. The writer generates the code automatically.

Customer ID: This area is for the Agent, for example used to store current number of customer.

Category ID: Can be used to store the application field information code.


Product ID: Storing the contents of the user ID number or data.

Data CRC: A 16 bits of CRC code is generated automatically by the writer.

Application Circuits

Tag

A tag consists of a PCB (or Mylar film) with printed coil, HT6720 and a housing. The housing can be of various shapes.




Note: The value of the antenna inductance is $11 \mu H$, however the optimum value will be changed slightly due to the variation of the internal resonance capacitor ($10 pF$ typically) during process.


For more application information about the reader, refer to Holtek's 13.56MHz RF ID reader data.

2-chip solution

Holtek Transponder Solution




Energy
Data




The symbols consist of a horizontal line with an arrow pointing left for Energy, and a horizontal line with an arrow pointing right for Data, with three curved lines between them representing RF coupling.

Holtek Reader Solution




Holtek low cost MCU:
HT48R05A/HT48R06A

Other Controller




1-chip solution (I)

Holtek Transponder Solution



Energy
←
Data


Holtek Reader Solution



Holtek Standard MCU:
HT48XXX/HT49XXX


1-chip solution (II)

Holtek Transponder Solution



Energy
←
Data

Holtek Reader Solution



Holtek Embedded MCU:
HT21XXX/HT84XXX/HT86XXX

Holtek Semiconductor Inc. (Headquarters)

No.3, Creation Rd. II, Science-based Industrial Park, Hsinchu, Taiwan
Tel: 886-3-563-1999
Fax: 886-3-563-1189
<http://www.holtek.com.tw>

Holtek Semiconductor Inc. (Sales Office)

11F, No.576, Sec.7 Chung Hsiao E. Rd., Taipei, Taiwan
Tel: 886-2-2782-9635
Fax: 886-2-2782-9636
Fax: 886-2-2782-7128 (International sales hotline)

Holtek Semiconductor (Shanghai) Inc.

7th Floor, Building 2, No.889, Yi Shan Rd., Shanghai, China
Tel: 021-6485-5560
Fax: 021-6485-0313
<http://www.holtek.com.cn>

Holtek Semiconductor (Hong Kong) Ltd.

Block A, 3/F, Tin On Industrial Building, 777-779 Cheung Sha Wan Rd., Kowloon, Hong Kong
Tel: 852-2-745-8288
Fax: 852-2-742-8657

Holmate Semiconductor, Inc.

46712 Fremont Blvd., Fremont, CA 94538
Tel: 510-252-9880
Fax: 510-252-9885
<http://www.holmate.com>

Copyright © 2001 by HOLTEK SEMICONDUCTOR INC.

The information appearing in this Data Sheet is believed to be accurate at the time of publication. However, Holtek assumes no responsibility arising from the use of the specifications described. The applications mentioned herein are used solely for the purpose of illustration and Holtek makes no warranty or representation that such applications will be suitable without further modification, nor recommends the use of its products for application that may present a risk to human life due to malfunction or otherwise. Holtek's products are not authorized for use as critical components in life support devices or systems. Holtek reserves the right to alter its products without prior notification. For the most up-to-date information, please visit our web site at <http://www.holtek.com.tw>.