## **Monolithic Integrated Circuit**

#### Application

Audio-Amplifier for portable radios, cassette recorders and general purposes.

#### Features

- Large supply voltage range  $V_S = 3 \dots 16 V$
- Low cross–over distortion
- Low harmonic distortion
- Adjustable voltage gain  $G_v = 34 \dots 54 \text{ dB}$
- Audio output power  $P_0 = 1.5 W$
- Connection possibility for an external capacitor to suppress hum voltage
- Bootstrap circuit




Figure 1 Block diagram and pin connections

#### **Absolute Maximum Ratings**

Reference point Pin 2, Pin 6

Parameters	Symbol	Value	Unit	
Supply voltage	Pin 4	Vs	16	V
Peak output current	Pin 3	I <sub>OM</sub>	850	mA
Power dissipation $T_{amb} = 50^{\circ}$	C	P <sub>tot</sub>	1	W
Junction temperature		Tj	150	°C
Storage temperature range		T <sub>stg</sub>	-25 +150	°C

#### **Thermal Resistance**

Parameters	Symbol	Maximum	Unit
Junction ambient	R <sub>thJA</sub>	100	k/W

#### **Electrical Characteristics**

 $V_S = 9$  V, reference point: Pin 2, Pin 6,  $G_v = 40$  dB, f = 1 kHz,  $R_L = 8 \Omega$ , d = 10 %,  $T_{amb} = 25$  °C, unless otherwise specified

Parameters	Test Condi	tions / Pin	Symbol	Min	Тур	Max	Unit
Supply voltage range		Pin 4	VS	3		16	V
Quiescent output voltage		Pin 3	V <sub>OB</sub>	3.9		4.7	V
Quiescent drain current							
$V_{\rm S} = 3 \text{ V}$	Figure 2	Pin 4	I <sub>SB</sub>	2	3	6	mA
$V_{\rm S} = 9 \ \rm V$			I <sub>SB</sub>	3.3	7.5	12	mA
V <sub>S</sub> = 16 V			I <sub>SB</sub>	3.3	7	10	mA
Output power			Po	0.9	1		W
Supply voltage rejection rati	0						
$V_{hum} = 0.35 V,$ $C_1 = 47 \mu F,$ $f_{hum} = 100 Hz$			SVR		30		dB
Input resistance		Pin 8	R <sub>i</sub>	800			kΩ
Band width (–3 dB)	Figure 2		В		100 28000		Hz
Distortion	Figure 2						
$P_0 = 50 \text{ mW}$			d		0.4	1	%
Voltage gain, closed loop							
$R_1 = 91 \Omega$			Gv	37	40	43	dB
Output noise voltage							
$R_G = 0,$ B = 22 22000 Hz		Pin 3	V <sub>no</sub>		250	600	μν




Figure 2 Test circuit for:  $P_0$ ,  $P_{tot}$ , d,  $V_{no}$ , B,  $G_v$  and application note

# TEMIC

′<sub>SB</sub>

10 ភ្នាA

8

6

4

2

0

Gvf

80

dB

60

40

20-

0⊥ 10


50


1**0**0

**500** Ω

R<sub>1</sub>----

#### **TELEFUNKEN Semiconductors**






U 413 B

**Preliminary Information** 

## U 413 B

# TELEFUNKEN Semiconductors

#### **Dimensions in mm**



Case 20 A 8 DIN 41866 DIP 8

#### **OZONE DEPLETING SUBSTANCES POLICY STATEMENT**

It is the policy of TEMIC TELEFUNKEN microelectronic GmbH to

- 1. Meet all present and future national and international statutory requirements and
- 2. Regularly and continuously improve the performance of our products, processes, distribution and operating systems with respect to their impact on the health and safety of our employees and the public, as well as their impact on the environment.

Of particular concern is the control or elimination of releases into the atmosphere of those substances which are known as ozone depleting substances (ODSs).

The Montreal Protocol (1987) and its London Amendments (1990) will soon severely restrict the use of ODSs and forbid their use within the next ten years. Various national and international initiatives are pressing for an earlier ban on these substances.

**TEMIC TELEFUNKEN microelectronic GmbH** semiconductor division has been able to use its policy of continuous improvements to eliminate the use of any ODSs listed in the following documents.

- 1. Annex A, B and list of transitional substances of the Montreal Protocol and the London Amendments respectively
- 2. Class I and II ozone depleting substances in the Clean Air Act Amendments of 1990 by the Environmental Protection Agency (EPA) in the USA and
- 3. Council Decision 88/540/EEC and 91/690/EEC Annex A, B and C (transitional substances) respectively.

TEMIC can certify that our semiconductors are not manufactured with and do not contain ozone depleting substances.

We reserve the right to make changes without further notice to improve technical design.

Parameters can vary in different applications. All operating parameters must be validated for each customer application by customer. Should Buyer use TEMIC products for any unintended or unauthorized application, Buyer shall indemnify TEMIC against all claims, costs, damages, and expenses, arising out of, directly or indirectly, any claim of personal damage, injury or death associated with such unintended or unauthorized use.

TEMIC TELEFUNKEN microelectronic GmbH, P.O.B. 3535, D-74025 Heilbronn, Germany Telephone: 49 (0)7131 67 2831, Fax Number: 49 (0)7131 67 2423

### **Preliminary Information**