


Cree® XLamp® XR LED Binning and Labeling

Cree XLamp LEDs combine the brightness of power LED chips with a rugged package capable of operating in excess of one watt. XLamp LEDs lead the solid-state lighting industry in brightness while providing a reflow-solderable design that is optimized for ease-of-use and thermal management. Lighting applications featuring XLamp LEDs maximize light output and increase design flexibility, while minimizing environmental impact.




This application note describes Cree's procedures for sorting XLamp LEDs by color (dominant wavelength or chromaticity) and brightness (flux) and then lists the order codes encompassing these color and brightness groups for easy reference.

Nomenclature

XLamp LEDs are tested and sorted into performance bins. A bin is specified by ranges of dominant wavelength and brightness. Sorted XLamp LEDs are packaged on reels. A reel contains lamps from one bin and is labeled with its bin code. For more information on packaging, see the XLamp LED Data Sheets.

XLamp LEDs are sold by order codes in combinations of bins called kits. Kits include a minimum of two dominant wavelength groups and two brightness groups. Order codes are configured in the following manner:




Color Codes							
RY = Royal blue	BL = Blue	CN = Cyan	GR = Green				
AM = Amber	RO = Red-orange	RD = Red	WT = White				

^{*} Global - an alternative white product that has higher efficacy with slightly lower color uniformity.

Kit number 0001 is always the order code encompassing the broadest range of color and brightness groups.



Order Codes Explanation



Performance Groups - Brightness

XLamp LEDs that are tested for luminous flux are placed into one of the following groups:

Group	Minimum Luminous Flux (lm) @ 350mA	Maximum Luminous Flux (lm) @ 350mA
F	10.7	13.9
G	13.9	18.1
Н	18.1	23.5
J	23.5	30.6
K	30.6	39.8
М	39.8	51.7
N	51.7	67.2

In order to minimize the perceived luminous flux variation among white lamps from the same reel, Cree bins to tighter luminous flux sub-groups. These sub-groups are defined below.

Group Code	Minimum Luminous Flux (lm)	Maximum Lumi- nous Flux (lm)
K2	30.6	35.2
K3	35.2	39.8
M2	39.8	45.7
M3	45.7	51.7
N2	51.7	56.8
N3	56.8	62.0
N4	62.0	67.2

Royal Blue XLamp LEDs are tested for radiant flux and are placed into one of the following groups:

Group	Minimum Radiant Flux (mW) @ 350 mA	Maximum Radiant Flux (mW) @ 350 mA
10	175	210
11	210	250
12	250	300
13	300	350

Performance Groups – Dominant Wavelength

Monochromatic XLamp LEDs are tested for dominant wavelength and placed into one of the following groups.

Color	DWL Group	Min. DWL (nm) @ 350mA	Max. DWL (nm) @ 350mA
Royal Blue	D4	455	460
Royal blue	D5	460	465
Blue	В3	465	470
blue	B4	470	475
Cyan	C2	500	505
Cyan	C3	505	510
	G2	520	525
Green	G3	525	530
	G4	530	535
Amber	A2	585	590
Affibei	A3	590	595
Red-Orange	03	610	615
Reu-Orange	04	615	620
	R2	620	625
Red	R3	625	630
	R4	630	635

Amber and red XLamp LEDs are binned according to forward voltage at the rated current. Cree's forward voltage groups are:

Forward Voltage Group	Minimum Forward Voltage @ 350 mA	Maximum Forward Voltage @ 350 mA
С	2.0	2.25
D	2.25	2.5
E	2.5	2.75
F	2.75	3.0



Performance Groups - Chromaticity

White XLamp LEDs are tested for chromaticity and placed into one of the regions defined by the bounding coordinates below.

White Color Region Coordinates - 5000K - 10000K

Region	х	у	Region	x	У	Region	x	У
	.292	.306		.329	.345		.329	.369
WA	.295	.297	WD	.329	.330	WG	.329	.345
VVA	.283	.284	VVD	.317	.319	WG	.316	.332
	.279	.291		.316	.332		.314	.355
	.306	.322		.301	.342	WH	.348	.384
WB	.308	.311	WE	.306	.322		.346	.359
WB	.295	.297	VVL	.292	.306		.329	.345
	.292	.306		.287	.321		.329	.369
	.316	.332		.314	.355		.329	.330
WC	.317	.319	WF	.316	.332	WJ	.329	.345
WC	.308	.311	VVI	.306	.322	۷۷۷	.346	.359
	.306	.322		.301	.342		.344	.342

White Color Region Coordinates - 3500K - 5000K

Region	х	у	Region	x	У	Region	х	у
	.344	.342		.387	.374		.3755	.372
TA	.346	.359	TD	.402	.382	TG	.380	.389
IA	.363	.368	10	.395	.364	16	.392	.391
	.360	.353		.382	.358		.387	.374
	.36	.353		.346	.359	тн	.392	.391
ТВ	.363	.368	TE	.348	.384		.387	.374
I B	.3755	.3715	I L	.367	.386		.402	.382
	.371	.3555		.363	.368		.409	.399
	.371	.3555		.363	.368			
TC	.3755	.3715	TF	.367	.386			
10	.387	.374		.380	.389			
	.382	.358		.3755	.372			




Performance Groups - Chromaticity (continued)

White Color Region Coordinates - 2600K - 3500K

Region	x	у	Region	x	У	Region	x	у
	.402	.382		.444	.399		.438	.412
C A	.416	.389	SD	.461	.404	20	.429	.394
SA	.409	.370	30	.450	.385	SG	.444	.399
	.395	.364		.435	.380		.453	.416
	.409	.370		.409	.399	SH	.444	.399
SB	.416	.389	SE	.402	.382		.461	.404
36	.429	.394	3L	.416	.389		.470	.420
	.420	.375		.424	.406		.453	.416
	.429	.394		.424	.406			
SC	.444	.399	SF	.416	.389			
30	.435	.380	эг	.429	.394			
	.420	.375		.438	.412			

Cree's Standard Chromaticity Regions Plotted on the 1931 CIE Curve





Standard Order Codes and Bins

The following tables list standard order code configurations and performance bins. Contact Cree at +1 919.313.5300 if custom order codes are required.

Standard Order Codes – Royal Blue							
Order Code	Bins		DWL (nm)		Radiant Flux (mW)		
Order Code	Color	Flux	Min.	Max.	Min.	Max.	
XR7090RY-L1-0001	D4, D5	10, 11, 12, 13	455	465	175	350	

Standard Order Codes - Blue							
Owdow Codo	Bi	Bins		DWL (nm)		Luminous Flux (lm)	
Order Code	Color	Flux	Min.	Max.	Min.	Max.	
XR7090BL-L1-0001	B3, B4	F, G, H, J	465	475	10.7	30.6	

Standard Order Codes – Cyan							
Oudou Codo	Bins		DWL (nm)		Luminous Flux (lm)		
Order Code	Color	Flux	Min.	Max.	Min.	Max.	
XR7090CN-L1-0001	C2, C3	K, M	500	510	30.6	51.7	

Standard Order Codes – Green						
Order Code	Bins		DWL (nm)		Luminous Flux (lm)	
	Color	Flux	Min.	Max.	Min.	Max.
XR7090GR-L1-0001	G2, G3, G4	K, M, N	520	535	30.6	67.2

Standard Order Codes – Amber							
Order Code	Bins		DWL (nm)		Luminous Flux (lm)		
	Color	Flux	Voltage	Min.	Max.	Min.	Max.
XR7090AM-L1-0001	A2, A3	J, K, M, N	C, D, E, F	585	595	23.5	67.2

Standard Order Codes – Red-Orange						
Order Code	Bins		DWL (nm)		Luminous Flux (lm)	
	Color	Flux	Min.	Max.	Min.	Max.
XR7090RO-L1-0001	D3, D4	K, M, N	610	620	30.6	67.2

Standard Order Codes - Red							
Order Code	Bins		DWL (nm)		Luminous Flux (lm)		
	Color	Flux	Voltage	Min.	Max.	Min.	Max.
XR7090RD-L1-0001	R2, R3, R4	Н, Ј, К, М	C, D, E, F	620	635	18.1	51.7



Standard Order Codes – White								
Order Code	В	Lum. Flux (lm)						
	Chromaticity	Flux	Min.	Max.				
XR7090WT-L1-0001	WA, WB, WC, WD, WE, WF, WG, WH, WJ	M2, M3, N2	39.8	56.8				
XR7090WT-L1-0002	WC,WD, WF, WG	M2, M3, N2	39.8	56.8				
XR7090WT-G1-0001	WA, WB, WC, WD, WE, WF, WG, WH, WJ	M2, M3, N2, N3	39.8	62				
XR7090WT-G1-0002	WC, WD, WF, WG	M2, M3, N2, N3	39.8	62				
XR7090WT-G1-0003	WB, WC, WD, WE, WF, WG, WH, WJ	N2, N3	51.7	62				
XR7090WT-L1-1001	TA, TB, TC, TD, TE, TF, TG, TH	K2, K3, M2, M3	30.6	51.7				
XR7090WT-L1-2001	SA, SB, SC, SD, SE, SF, SG, SH	K2, K3, M2	30.6	45.7				