MAAM-008970



Satellite Communications Single Ended 2-Way Active Splitter 950 - 2150 MHz

Rev. V1

Features

- 2-Way Splitter
- Single Ended Input and Outputs
- 75 Ω Impedance
- 4.8 dB Gain
- Single +5 Volt Supply
- Lead-Free 3 mm 12-Lead PQFN Package
- Halogen-Free "Green" Mold Compound
- RoHS* Compliant and 260°C Reflow Compatible

Description

M/A-COM Tech's MAAM-008970 2-way active splitter is a GaAs MMIC which exhibits low noise figure and distortion in a lead-free PQFN plastic package. The MAAM-008970 employs a low noise, linearity amplifier and power splitter functionality. The design features 75 Ω inputs and outputs.

The MAAM-008970 is ideally suited for satellite communications multi-tuner set top boxes, and other broadband based appliances.


The MAAM-008970 is fabricated using M/A-COM Tech's PHEMT process to realize low noise and low distortion. The process features full passivation for robust performance and reliability.

Ordering Information^{1,2}

Part Number	Package
MAAM-008970-TR1000	1000 piece reel
MAAM-008970-TR3000	3000 piece reel
MAAM-008970-001SMB	Sample Test Board

- 1. Reference Application Note M513 for reel size information.
- 2. All sample boards include 5 loose parts.

Functional Schematic



Pin Configuration³

Pin No.	Pin Name	Description		
1	N/C	No Connection		
2	IN	RF Input		
3	N/C	No Connection		
4	N/C	No Connection		
5	N/C	No Connection		
6	N/C	No Connection		
7	OUT2	RF Output 2		
8	N/C	No Connection		
9	OUT1	RF Output 1		
10	N/C	No Connection		
11	N/C	No Connection		
12	N/C	No Connection		
13	Paddle ³			

^{3.} The exposed pad centered on the package bottom must be connected to RF and DC ground.

^{*} Restrictions on Hazardous Substances, European Union Directive 2002/95/EC.

[•] India Tel: +91.80.43537383

MAAM-008970



Satellite Communications Single Ended 2-Way Active Splitter 950 - 2150 MHz

Rev. V1

Electrical Specifications: Freq: 2150 MHz, $T_A = 25^{\circ}C$, $V_{DD} = +5$ Volts, $Z_0 = 75 \Omega$

Parameter	Test Conditions	Units	Min.	Тур.	Max.
Gain	In to Out1, In to Out2	dB	4.0	4.8	5.8
Gain Flatness	In to Out1, In to Out2	dB	_	0.3	_
Noise Figure	In to Out1, In to Out2	dB		5.0	_
Input Return Loss	Input	dB		12	
Output Return Loss	Output	dB	_	12	_
Reverse Isolation	Out1 to In, Out2 to In	dB	_	18	_
Output to Output Isolation	Out1 to Out2	dB		23	
Output Power at 1 dB Compression, P1dB	1450 MHz	dBm	_	7	_
Output 3rd Order Intercept Point, OIP3	1450 MHz, P _{IN} = 0 dBm, 6 MHz Spacing	dBm	_	17	_
Output 2nd Order Intercept Point, OIP2	1450 MHz, P _{IN} = 0 dBm, 6 MHz Spacing	dBm	_	30	_
I _{DD}	V _{DD} = + 5 Volts	mA	_	60	75

Absolute Maximum Ratings 4,5,6

Parameter	Absolute Maximum
Input Power	+12 dBm
Vbias	+10.0 V
Operating Temperature	0°C to +85°C
Junction Temperature ⁷	+150°C
Storage Temperature	-65°C to +125°C

- 4. Exceeding any one or combination of these limits may cause permanent damage to this device.
- 5. M/A-COM does not recommend sustained operation near these survivability limits.
- 6. These operating conditions will ensure MTTF > 1×10^6 hours.
- 7. Junction Temperature $(T_J) = T_A + \Theta jc * (V * I)$ Typical thermal resistance (Θjc) = 148 °C/W.

a) For $T_A = 25^{\circ}C$,

 $T_J = 69 \, ^{\circ}\text{C} \ @ 5.0 \, \text{V}, 60 \, \text{mA}$

b) For $T_A = 85^{\circ}C$,

T_J = 126 °C @ 5.0 V, 55 mA

Handling Procedures

Please observe the following precautions to avoid damage:

Static Sensitivity

Gallium Arsenide Integrated Circuits are sensitive to electrostatic discharge (ESD) and can be damaged by static electricity. Proper ESD control techniques should be used when handling these devices.

• India Tel: +91.80.43537383 Visit www.macomtech.com for additional data sheets and product information.


· China Tel: +86.21.2407.1588




Satellite Communications Single Ended 2-Way Active Splitter 950 - 2150 MHz

Rev. V1


Recommended PCB



PCB Land Pattern



Schematic Including Off-Chip Components



Off-Chip Component Values

Component	Value	Package
C1 - C5	1000 pF	0402
C6 - C7	0.01 μF	0402
L1	4.7 nH	0402
L2, L3	2 nH	0402
L4, L5	100 nH	1008
R1, R2	480 Ω	0402
R3, R4	75 Ω	0402

Visit www.macomtech.com for additional data sheets and product information.

[•] China Tel: +86.21.2407.1588




Satellite Communications Single Ended 2-Way Active Splitter 950 - 2150 MHz


Rev. V1

Typical Performance Curves

Gain_OUT1 & OUT2




Input Return Loss




Reverse Isolation to 3 GHz


Commitment to produce in volume is not guaranteed.




Gain_OUT1 & OUT2 to 3 GHz



Output Return Loss (Typical both Outputs)



Noise Figure (Typical both Outputs)



- ADVANCED: Data Sheets contain information regarding a product M/A-COM Technology Solutions is considering for development. Performance is based on target specifications, simulated results, and/or prototype measurements. Commitment to develop is not guaranteed.

 PRELIMINARY: Data Sheets contain information regarding a product M/A-COM Technology Solutions has under development. Performance is based on engineering tests. Specifications are typical. Mechanical outline has been fixed. Engineering samples and/or test data may be available.
- North America Tel: 800.366.2266
 India Tel: +91.80.43537383
 Europe Tel: +353.21.244.6400
 China Tel: +86.21.2407.1588
 Visit www.macomtech.com for additional data sheets and product information.




Satellite Communications Single Ended 2-Way Active Splitter 950 - 2150 MHz


Rev. V1

Typical Performance Curves


Out - Out Isolation



Out - Out Isolation to 3 GHz



Lead-Free 3 mm 12-Lead PQFN[†]



Reference Application Note M538 for lead-free solder reflow recommendations. Meets JEDEC moisture sensitivity level 1 requirements. Plating is 100% matte tin plating over copper.

• India Tel: +91.80.43537383

• China Tel: +86.21.2407.1588 Visit www.macomtech.com for additional data sheets and product information.