
Absolute Maximum Ratings

Parameter	Symbol	Limits	Unit
Input voltage	Vi	170	V
Output current	lo	30	mApk
ESD endurance	Vsurge	2	kV
Operating temperature range	Topr	-20 ~ +80	°C
Storage temperature range	Tstg	−20 ~ +85	°C

Dimension(Unit : mm)




Electrical Characteristics


Parameter	Symbol	Min.	Тур.	Max.	Unit	Conditions	
Input voltage range	Vi	113	141	170	V	DC(80~120VAC)	
Output voltage	Vo	4.7	5.0	5.3	V	Vi=141V, Io=15mA	
Output current	lo	0	_	30	mA	Vi=141V *1	
Line regulation	Vr	-	0.1	0.3	V	Vi=113~170V, Io=15mA	
Load regulation	VI	_	0.15	0.3	V	Vi=141V, Io=0~15mA *2	
Output ripple voltage	Vp	-	0.05	0.15	Vp-p	Vi=141V, Io=15mA	
Power conversion effciency	η	25	33	_	%	Vi=141V, Io=30mA *2	

- *1 Maximum output current varies depending on ambient temperature; please refer to derating curve
- *2 Please refer to Load regulation, Conversion effciency.


Derating Curve



Switching Frequency




Application circuit



For acutual usage, Please kindly evaluate and confirm our part mounted in your product, Especially, Please make sure to confirm whether the load current exceed Max. rated current by using the current probe.

Conversion Efficiency



External components setting

FUSE: Fuse C1: Capacitor for input voltage smoothing Please make sure to use quick acting fuse 0.5A

Capacitance : $3.3\mu F\sim 22\mu F$ Rated voltage : 200V or higher Ripple current is 0.13Arms above.

C2: For noise terminal voltage reduction Capacitance : $0.1\mu F\sim 0.22\mu F$ Rated voltage : 200V or higher Film capacitor or ceramic capacitor. Reduce the noise terminal voltage.

Input terminal Vi(141VDC

COMMON

The constant value should be evaluated in the set.

C3: Capacitor for Output

Capacitance : $100\mu F\sim 470\mu F$ Rated voltage : 25V or higher, ESR is 0.39Ω max. Ripple current is 0.1Arms above.

voltage smooting

D1: Rectifier diode

Output noise voltage is influenced. Please evaluate it in the actual set. In the absolute maximum ratings, the reverse peak voltage should be

400V or higher, the average rectifying current should be 0.5A or higher, and the peak surge current should be 20A or higher. (Full-wave rectifier can be used in our part.)

R1: For noise terminal

10Ω~22Ω 1/4W


voltage reduction

Reduce the noise terminal voltage. The constant value should be evaluated


ZNR: Varistor

Varistor must be used. It protects this part from lightning surge and static

Load Regulation



Surface Temperature Rising



Precautions on Use of ROHM Power Module

Safety Precautions

- 1) The products are designed and produced for application in ordinary electronic equipment (AV equipment, OA equipment, telecommunication equipment, home appliances, amusement equipment etc.). If the products are to be used in devices requiring extremely high reliability (medical equipment, transport equipment, aircraft/spacecraft, nuclear power controllers, fuel controllers, car equipment including car accessories, safety devices, etc.) and whose malfunction or operational error may endanger human life and sufficient fail-safe measures, please consult with the Company's sales staff in advance. If product malfunctions may result in serious damage, including that to human life, sufficient fail-safe measures must be taken, including the following:
 - [a] Installation of protection circuits or other protective devices to improve system safety
 - [b] Installation of redundant circuits in the case of single-circuit failure
- 2) The products are designed for use in a standard environment and not in any special environments. Application of the products in a special environment can deteriorate product performance. Accordingly, verification and confirmation of product performance, prior to use, is recommended if used under the following conditions:
 - [a] Use in various types of liquid, including water, oils, chemicals, and organic solvents
 - [b] Use outdoors where the products are exposed to direct sunlight, or in dusty places
 - [c] Use in places where the products are exposed to sea winds or corrosive gases, including Cl2, H2S, NH3, SO2, and NO2
 - [d] Use in places where the products are exposed to static electricity or electromagnetic waves
 - [e] Use in proximity to heat-producing components, plastic cords, or othe flammable items
 - [f] Use involving sealing or coating the products with resin or other coating materials
 - [g] Use involving unclean solder or use of water or water-soluble cleaning agents for cleaning after soldering
 - [h] Use of the products in places subject to dew condensation
- 3) The products are not radiation resistant.
- 4) The Company is not responsible for any problems resulting from use of the products under conditions not recommended herein.
- 5) The Company should be notified of any product safety issues. Moreover, product safety issues should be periodically monitored by the customer.

Precautions Regarding Application Example and External Circuits

- 1) If change is made to the constant of an external circuit, allow a sufficient margin due to variations of the characteristics of the products and external components, including transient characteristics, as well as static characteristics. Please be informed that the Company has not conducted investigations on whether or not particular changes in the application examples or external circuits would result in the infringement of patent rights of a third party.
- 2) The application examples, their constants, and other types of information contained herein are applicable only when the products are used in accordance with standard methods.
 - Therefore, if mass production is intended, sufficient consideration to external conditions must be made.

Prohibitions Regarding Industrial Property

- 1) These Specifications contain information related to the Company's industrial property. Any use of them other than pertaining to the usage of appropriate products is not permitted. Duplication of these Specifications and its disclosure to a third party without the Company's permission is prohibited.
- 2) Information and data on products, including application examples, contained in these specifications are simply for reference; the Company does not guarantee any industrial property rights, intellectual property rights, or any other rights of a third party regarding this information or data. Accordingly, the Company does not bear any responsibility for:
 - [a] infringement of the intellectual property rights of a third party
 - [b] any problems incurred by the use of the products listed herein.
- 3) The Company prohibits the purchaser of its products to exercise or use the intellectual property rights, industrial property rights, or any other rights that either belong to or are controlled by the Company, other than the right to use, sell, or dispose of the products.

