

MOS FIELD EFFECT TRANSISTOR

2SK3354

SWITCHING N-CHANNEL POWER MOS FET

DESCRIPTION

The 2SK3354 is N-channel MOS Field Effect Transistor designed for high current switching applications.

FEATURES

• Super low on-state resistance:

 $R_{DS(on)1}=8.0\,m\Omega$ MAX. (VGs = 10 V, ID = 42 A)

 $R_{DS(on)2} = 12 \text{ m}\Omega$ MAX. (Vgs = 4 V, ID = 42 A)

- Low Ciss: Ciss = 6300 pF TYP.
- Built-in gate protection diode

ORDERING INFORMATION

PART NUMBER	PACKAGE
2SK3354	TO-220AB
2SK3354-S	TO-262
2SK3354-ZJ	TO-263
2SK3354-Z	TO-220SMD ^{Note}

Note TO-220SMD package is produced only in Japan.

(TO-220AB)

ABSOLUTE MAXIMUM RATINGS (TA = 25°C)

Drain to Source Voltage (V _{GS} = 0 V)	Voss	60	V
Gate to Source Voltage (V _{DS} = 0 V)	VGSS(AC)	±20	V
Drain Current (DC) (Tc = 25°C)	I _{D(DC)}	±83	Α
Drain Current (pulse) Note1	D(pulse)	±332	Α
Total Power Dissipation (Tc = 25°C)	P _{T1}	100	W
Total Power Dissipation (T _A = 25°C)	P _{T2}	1.5	W
Channel Temperature	T_ch	150	°C
Storage Temperature	T_{stg}	-55 to +150	°C
Single Avalanche Current Note2	las	55	Α
Single Avalanche Energy Note2	Eas	302	mJ

Notes 1. PW \leq 10 μ s, Duty cycle \leq 1%

2. Starting Tch = 25°C, VDD = 30 V , RG = 25 Ω , VGS = 20 \rightarrow 0 V



(TO-262)



(TO-263, TO-220SMD)



The information in this document is subject to change without notice. Before using this document, please confirm that this is the latest version. Not all devices/types available in every country. Please check with local NEC representative for availability and additional information.




ELECTRICAL CHARACTERISTICS (TA = 25°C)


CHARACTERISTICS	SYMBOL	TEST CONDITIONS	MIN.	TYP.	MAX.	UNIT
Zero Gate Voltage Drain Current	Ipss	V _{DS} = 60 V, V _{GS} = 0 V			10	μА
Gate Leakage Current	lgss	Vgs = ±20 V, Vps = 0 V			±10	μА
Gate Cut-off Voltage	V _{GS(off)}	V _{DS} = 10 V, I _D = 1 mA	1.5	2.0	2.5	V
Forward Transfer Admittance	yfs	V _{DS} = 10 V, I _D = 42 A	35	59		S
Drain to Source On-state Resistance	RDS(on)1	Vgs = 10 V, ID = 42 A		6.3	8.0	mΩ
	RDS(on)2	V _G S = 4 V, I _D = 42 A		8.0	12	mΩ
Input Capacitance	Ciss	V _{DS} = 10 V		6300		pF
Output Capacitance	Coss	V _G S = 0 V		1000		pF
Reverse Transfer Capacitance	Crss	f = 1 MHz		490		pF
Turn-on Delay Time	td(on)	V _{DD} = 30 V, I _D = 42 A		100		ns
Rise Time	tr	V _G S = 10 V		1500		ns
Turn-off Delay Time	td(off)	$R_G = 10 \Omega$		300		ns
Fall Time	tf			440		ns
Total Gate Charge	Q _G	V _{DD} = 48 V		106		nC
Gate to Source Charge	Qgs	V _G S = 10 V		20		nC
Gate to Drain Charge	Q _{GD}	ID = 83 A		30		nC
Body Diode Forward Voltage	VF(S-D)	IF = 83 A, VGS = 0 V		1.0		V
Reverse Recovery Time	trr	IF = 83 A, VGS = 0 V		55		ns
Reverse Recovery Charge	Qrr	di/dt = 100 A/μs		100		nC


TEST CIRCUIT 1 AVALANCHE CAPABILITY

$\begin{array}{c} \text{D.U.T.} \\ \text{RG} = 25 \ \Omega \\ \text{PG.} \\ \text{VGS} = 20 \rightarrow 0 \ V \end{array}$



TEST CIRCUIT 2 SWITCHING TIME







TEST CIRCUIT 3 GATE CHARGE




TYPICAL CHARACTERISTICS(TA = 25°C)





FORWARD BIAS SAFE OPERATING AREA 1000 Leading 100 Lead

 $V_{\text{\scriptsize DS}}$ - Drain to Source Voltage - V




TRANSIENT THERMAL RESISTANCE vs. PULSE WIDTH


3


PW - Pulse Width - s

FORWARD TRANSFER CHARACTERISTICS




DRAIN CURRENT vs. DRAIN TO SOURCE VOLTAGE







DRAIN TO SOURCE ON-STATE RESISTANCE vs. GATE TO SOURCE VOLTAGE




DRAIN TO SOURCE ON-STATE RESISTANCE vs. DRAIN CURRENT





GATE CUT-OFF VOLTAGE vs. CHANNEL TEMPERATURE






























★ PACKAGE DRAWINGS (Unit: mm)


1) TO-220AB(MP-25)




2) TO-262(MP-25 Fin Cut)



3) TO-263 (MP-25ZJ)




4) TO-220SMD(MP-25Z)^{Note}



EQUIVALENT CIRCUIT

Note This package is produced only in Japan.



Remark

The diode connected between the gate and source of the transistor serves as a protector against ESD. When this device actually used, an additional protection circuit is externally required if a voltage exceeding the rated voltage may be applied to this device.

- The information in this document is current as of July, 2002. The information is subject to change without notice. For actual design-in, refer to the latest publications of NEC's data sheets or data books, etc., for the most up-to-date specifications of NEC semiconductor products. Not all products and/or types are available in every country. Please check with an NEC sales representative for availability and additional information.
- No part of this document may be copied or reproduced in any form or by any means without prior written consent of NEC. NEC assumes no responsibility for any errors that may appear in this document.
- NEC does not assume any liability for infringement of patents, copyrights or other intellectual property rights of
 third parties by or arising from the use of NEC semiconductor products listed in this document or any other
 liability arising from the use of such products. No license, express, implied or otherwise, is granted under any
 patents, copyrights or other intellectual property rights of NEC or others.
- Descriptions of circuits, software and other related information in this document are provided for illustrative purposes in semiconductor product operation and application examples. The incorporation of these circuits, software and information in the design of customer's equipment shall be done under the full responsibility of customer. NEC assumes no responsibility for any losses incurred by customers or third parties arising from the use of these circuits, software and information.
- While NEC endeavours to enhance the quality, reliability and safety of NEC semiconductor products, customers
 agree and acknowledge that the possibility of defects thereof cannot be eliminated entirely. To minimize
 risks of damage to property or injury (including death) to persons arising from defects in NEC
 semiconductor products, customers must incorporate sufficient safety measures in their design, such as
 redundancy, fire-containment, and anti-failure features.
- NEC semiconductor products are classified into the following three quality grades:
 - "Standard", "Special" and "Specific". The "Specific" quality grade applies only to semiconductor products developed based on a customer-designated "quality assurance program" for a specific application. The recommended applications of a semiconductor product depend on its quality grade, as indicated below. Customers must check the quality grade of each semiconductor product before using it in a particular application.
 - "Standard": Computers, office equipment, communications equipment, test and measurement equipment, audio and visual equipment, home electronic appliances, machine tools, personal electronic equipment and industrial robots
 - "Special": Transportation equipment (automobiles, trains, ships, etc.), traffic control systems, anti-disaster systems, anti-crime systems, safety equipment and medical equipment (not specifically designed for life support)
 - "Specific": Aircraft, aerospace equipment, submersible repeaters, nuclear reactor control systems, life support systems and medical equipment for life support, etc.

The quality grade of NEC semiconductor products is "Standard" unless otherwise expressly specified in NEC's data sheets or data books, etc. If customers wish to use NEC semiconductor products in applications not intended by NEC, they must contact an NEC sales representative in advance to determine NEC's willingness to support a given application.

(Note)

- (1) "NEC" as used in this statement means NEC Corporation and also includes its majority-owned subsidiaries.
- (2) "NEC semiconductor products" means any semiconductor product developed or manufactured by or for NEC (as defined above).

M8E 00.4