





# Rectifiers, General Purpose

(Continued)

$I_O$ (AMPS)	2.0		3.0		
@ $T_A$ (°C)	75	50	75	55	75
$I_{FSM}$ (AMPS)	50	50	200	100	125
					
CASE	GPR-1A	DO-15	DO-201AD	GPR-3A	
$V_{RRM}$ (VOLTS)					
50			1N5400		
100	CPR2-010	CR2-010	1N5401		
200	CPR2-020	CR2-020	1N5402	1N5550	1N5624
300			1N5403		
400	CPR2-040	CR2-040	1N5404	1N5551	1N5625
500			1N5405		
600	CPR2-060	CR2-060	1N5406	1N5552	1N5626
800	CPR2-080	CR2-080	1N5407	1N5553	1N5627
1000	CPR2-100	CR2-100	1N5408	1N5554	
1200	CPR2-120	CR2-120			
1400		CR2-140			
1600		CR2-160			

$V_F$ MAX @ $I_F=I_O$	1.2V	1.1V	1.1V	1.1V	1.0V
-----------------------	------	------	------	------	------

$I_R$ MAX @ $V_{RRM}$	5.0 $\mu$ A	10 $\mu$ A	10 $\mu$ A	1.0 $\mu$ A	5.0 $\mu$ A
-----------------------	-------------	------------	------------	-------------	-------------