

| Parameter                              | Rating | Units          |
|--|--------|----------------|
| Breakdown Voltage - $BV_{CEO}$         | 30     | V <sub>P</sub> |
| Current Transfer Ratio - CTR (typical) | 8500   | %              |
| Saturation Voltage - $V_{CE(sat)}$     | 1      | V              |
| Input Control Current - $I_F$          | 1      | mA             |

## Features

- Unidirectional Input
- Small 6-Pin Package, Thru-Hole or Surface Mount
- 100mA Continuous Load Rating
- 3750V<sub>rms</sub> Input/Output Isolation
- Machine Insertable, Wave Solderable
- Surface Mount Tape & Reel Packaging Available

## Description

LDA111 is a unidirectional input optocoupler with a Darlington transistor output. The LDA111 has a minimum current transfer ratio (CTR) of 300% with a maximum value of 30,000%.

## Approvals

- UL Recognized Component: File # E76270
- CSA Certified Component: Certificate # 1175739


## Ordering Information

| Part Number | Description                     |
|-------------|---------------------------------|
| LDA111      | 6-Pin DIP (50/tube)             |
| LDA111S     | 6-Pin Surface Mount (50/tube)   |
| LDA111STR   | 6-Pin Surface Mount (1000/Reel) |

## Applications

- Telecom Switching
- Tip/Ring Circuits
- Modem Switching (Laptop, Notebook, Pocket Size)
- Loop Detect
- Ringing Detect
- Current Sensing

## Pin Configuration



## Absolute Maximum Ratings

| Parameter                            | Ratings     | Units            |
|--------------------------------------|-------------|------------------|
| Breakdown Voltage                    | 30          | V <sub>P</sub>   |
| Reverse Input Voltage                | 5           | V                |
| Input Control Current                | 100         | mA               |
| Peak (10ms)                          | 1           | A                |
| Power Dissipation                    |             |                  |
| Input Power Dissipation <sup>1</sup> | 150         | mW               |
| Phototransistor <sup>2</sup>         | 150         |                  |
| Isolation Voltage, Input to Output   | 3750        | V <sub>rms</sub> |
| Operational Temperature              | -40 to +85  | °C               |
| Storage Temperature                  | -40 to +125 | °C               |

<sup>1</sup> Derate Linearly 1.33 mW/°C<sup>2</sup> Derate Linearly 2.0 mW/°C

Electrical absolute maximum ratings are at 25°C


*Absolute Maximum Ratings are stress ratings. Stresses in excess of these ratings can cause permanent damage to the device. Functional operation of the device at conditions beyond those indicated in the operational sections of this data sheet is not implied.*

## Electrical Characteristics











| Parameter                            | Conditions                                  | Symbol               | Min | Typ  | Max   | Units |
|--------------------------------------|---|----------------------|-----|------|-------|-------|
| <b>Output Characteristics @ 25°C</b> |   |                      |     |      |       |       |
| Phototransistor Breakdown Voltage    | I <sub>C</sub> = 100µA                      | BV <sub>CEO</sub>    | 30  | 85   | -     | V     |
| Phototransistor Dark Current         | V <sub>CEO</sub> = 5V, I <sub>F</sub> = 0mA | I <sub>CEO</sub>     | -   | 50   | 500   | nA    |
| Saturation Voltage                   | I <sub>C</sub> = 3mA, I <sub>F</sub> = 1mA  | V <sub>CE(sat)</sub> | -   | -    | 1     | V     |
| Current Transfer Ratio               | I <sub>F</sub> = 1mA, V <sub>CE</sub> = 2V  | CTR                  | 300 | 8500 | 30000 | %     |
| Output Capacitance                   | 25V, f = 1MHz                               | C <sub>OUT</sub>     | -   | 3    | -     | pF    |
| <b>Input Characteristics @ 25°C</b>  |   |                      |     |      |       |       |
| Input Control Current                | I <sub>C</sub> = 3mA, V <sub>CE</sub> = 2V  | I <sub>F</sub>       | -   | 0.07 | 1     | mA    |
| Input Voltage Drop                   | I <sub>F</sub> = 5mA                        | V <sub>F</sub>       | 0.9 | 1.2  | 1.4   | V     |
| Reverse Input Current                | V <sub>R</sub> = 5V                         | I <sub>R</sub>       | -   | -    | 10    | µA    |
| <b>Common Characteristics @ 25°C</b> |   |                      |     |      |       |       |
| Capacitance, Input to Output         | -   | C <sub>I/O</sub>     | -   | 3    | -     | pF    |

## Switching Characteristics @ 25°C

| Characteristic | Symbol           | Test Condition   | Typ | Units |
|----------------|------------------|--|-----|-------|
| Turn-On Time   | t <sub>ON</sub>  | V <sub>CC</sub> =5V, I <sub>F</sub> =1mA, R <sub>L</sub> =500Ω | 8   | µs    |
| Turn-Off Time  | t <sub>OFF</sub> |  | 345 |       |



## PERFORMANCE DATA\*



\*The Performance data shown in the graphs above is typical of device performance. For guaranteed parameters not indicated in the written specifications, please contact our application department.

## Manufacturing Information

### Soldering

For proper assembly, the component must be processed in accordance with the current revision of IPC/JEDEC standard J-STD-020. Failure to follow the recommended guidelines may cause permanent damage to the device resulting in impaired performance and/or a reduced lifetime expectancy.




### Washing

Clare does not recommend ultrasonic cleaning or the use of chlorinated solvents.




## MECHANICAL DIMENSIONS

### 6-Pin DIP Thru-Hole Package






### PC Board Pattern




Dimensions  
mm  
(inches)

### 6-Pin Surface Mount Package ("S" Suffix)




### Recommended PCB Land Pattern



Dimensions  
mm  
(inches)

## MECHANICAL DIMENSIONS

### Tape and Reel Packaging for 6-Pin "S" Suffix Parts



For additional information please visit our website at: [www.clare.com](http://www.clare.com)

Clare, Inc. makes no representations or warranties with respect to the accuracy or completeness of the contents of this publication and reserves the right to make changes to specifications and product descriptions at any time without notice. Neither circuit patent licenses nor indemnity are expressed or implied. Except as set forth in Clare's Standard Terms and Conditions of Sale, Clare, Inc. assumes no liability whatsoever, and disclaims any express or implied warranty, relating to its products including, but not limited to, the implied warranty of merchantability, fitness for a particular purpose, or infringement of any intellectual property right.

The products described in this document are not designed, intended, authorized or warranted for use as components in systems intended for surgical implant into the body, or in other applications intended to support or sustain life, or where malfunction of Clare's product may result in direct physical harm, injury, or death to a person or severe property or environmental damage. Clare, Inc. reserves the right to discontinue or make changes to its products at any time without notice.