# MIDDLING VOLTAGE **FAST-SWITCHING NPN POWER TRANSISTOR**

#### DESCRIPTION


The UTC 4124D is a middling voltage NPN power transistor. it uses UTC's advanced technology to provide customers with high switching speed and high reliability, etc.

The UTC 4124D is suitable for electronic ballasts, commonly power amplifier circuit and energy-saving light etc.

#### **FEATURES**

- \* High switching speed
- \* High reliability







## **ORDERING INFORMATION**

Ordering Number		Doolsono	Pin Assignment			Doolsing	
Lead Free	Halogen Free	Package	1	2	3	Packing	
4124DL-T92-B	4124DG-T92-B	TO-92	В	С	E	Tape Box	
4124DL-T92-K	4124DG-T92-K	TO-92	В	С	Е	Bulk	
4124DL-T92-R	4124DG-T92-R	TO-92	В	С	E	Tape Reel	
4124DL-T60-K	4124DG-T60-K	TO-126	В	С	Е	Bulk	

Note: Pin Assignment: B: Base C: Collector E: Emitter





www.unisonic.com.tw 1 of 3

## ■ ABSOLUTE MAXIMUM RATINGS (T<sub>C</sub>=25°C)

PARAMETER		SYMBOL	RATINGS	UNIT
Collector-Base Voltage (V <sub>BE</sub> =0)		V <sub>CES</sub>	350	V
Collector-Emitter Voltage (I <sub>B</sub> =0)		$V_{CEO}$	200	V
Emitter-Base Voltage		$V_{EBO}$	7	V
Continuous Collector Current	DC	lc	2	Α
	Pulse (Note 2)	I <sub>CP</sub>	I <sub>CP</sub> 4	
Base Current	DC	$I_{B}$	1	Α
	Pulse (Note 2)	I <sub>BP</sub>	2	Α
Tatal Biodication	TO-92	Б	1.5	W
Total Dissipation	TO-126	Pc	20	W
Junction Temperature		TJ	150	°C
Storage Temperature Range		T <sub>STG</sub>	-55~+150	°C

Note: 1. Absolute maximum ratings are stress ratings only and functional device operation is not implied. Absolute maximum ratings are those values beyond which the device could be permanently damaged.

## **■ THERMAL CHARACTERISTICS**


PARAMETER		SYMBOL	RATINGS	UNIT	
Junction to Case	TO-92	0	80	°C/W	
	TO-126	θJC	6.25	°C/W	


## **■ ELECTRICAL CHARACTERISTICS**


PARAMETER	SYMBOL	TEST CONDITIONS	MIN	TYP	MAX	UNIT
Collector-Base Breakdown Voltage	$BV_CBO$	I <sub>C</sub> =1mA, I <sub>B</sub> =0	350			V
Collector-Emitter Breakdown Voltage	$BV_CEO$	I <sub>C</sub> =10mA, I <sub>B</sub> =0	200			V
Emitter-Base Breakdown Voltage	$BV_{EBO}$	I <sub>E</sub> =1mA, I <sub>C</sub> =0	7			V
Collector Cut-Off Current	I <sub>CBO</sub>	V <sub>CB</sub> =350V, I <sub>E</sub> =0			100	μΑ
Collector-Emitter Cut-Off Current	I <sub>CEO</sub>	V <sub>CE</sub> =200V, I <sub>B</sub> =0			50	μΑ
Emitter Cut-Off Current	I <sub>EBO</sub>	$V_{EB}$ =7V, $I_C$ =0			10	μΑ
0.111	$V_{CE(SAT)1}$	I <sub>C</sub> =0.5A, I <sub>B</sub> =0.1A			0.8	V
Collector-Emitter Saturation Voltage	$V_{CE(SAT)2}$	I <sub>C</sub> =1.5A, I <sub>B</sub> =0.5A			1.0	V
Base-Emitter Saturation Voltage	$V_{BE(SAT)}$	I <sub>C</sub> =1A, I <sub>B</sub> =0.25A			1.5	V
DO 0	h <sub>FE1</sub>	I <sub>C</sub> =0.2A,V <sub>CE</sub> =5V	8		50	
DC Current Gain	h <sub>FE2</sub>	I <sub>C</sub> =2A,V <sub>CE</sub> =5V	5			
Transition Frequency	f <sub>T</sub>	I <sub>C</sub> =0.5A, V <sub>CE</sub> =10V	4			MHz
Storage Time	t <sub>S</sub>	\\ -24\\   -0.5A   -   -0.4A			4	μs
Fall Time	t <sub>F</sub>	$V_{CC}$ =24V, $I_{C}$ =0.5A, $I_{B1}$ =- $I_{B2}$ =0.1A			0.7	μs

<sup>2.</sup> Pulse Test: Pulse Width=5.0ms, Duty Cycle<10%.

## **■ TYPICAL CHARACTERISTICS**







UTC assumes no responsibility for equipment failures that result from using products at values that exceed, even momentarily, rated values (such as maximum ratings, operating condition ranges, or other parameters) listed in products specifications of any and all UTC products described or contained herein. UTC products are not designed for use in life support appliances, devices or systems where malfunction of these products can be reasonably expected to result in personal injury. Reproduction in whole or in part is prohibited without the prior written consent of the copyright owner. The information presented in this document does not form part of any quotation or contract, is believed to be accurate and reliable and may be changed without notice.