HFE28

CONTACT DATA

HIGH POWER LATCHING RELAY



Features

- Latching relay
- 100A switching capability at Res.load
- According to the fault current and electrical life test of IEC 62055-31: UC1, UC2, UC3 (please see below table and notes2)
- AC-voltage driving is feasible
- 4kV dielectric strength (between coil and contacts)
- Environmental friendly product (RoHS compliant)
- Outline Dimensions: (66.0 x 75.0 x 23.5) mm

SONTAGE BATA	
Contact arrangement	2A, 2B, 2SH, 2SD
Contact resistance	Typ.:0.35mΩ max.(at 100A) ⁽¹⁾
Contact material	AgSnO ₂
Contact rating (Res. load)	100A 277VAC/28VDC
Max. switching voltage	440VAC
Max. switching current	120A

Notes: (1) Typical value: Sampling quantity for contact resistance shall not less than 20 pcs, take the average value from 5 continous measurements for each sample.

CHARACTERISTICS

Max. switching power

Mechanical endurance

Insulation r	esistance	1000MΩ (at 500VDC)		
Dielectric	Between coil & contacts	4000VAC 1min		
strength	Between open contacts	2500VAC 1min		
Creepage	distance	9.6mm		
Operate tin	ne (at nomi. volt.)	20ms max.		
Release tir	ne (at nomi. volt.)	20ms max.		
Shock	Functional	98m/s²		
resistance	Destructive	980m/s ²		
Vibration resistance		10Hz to 55Hz 1.5mm DA		
Humidity		5% to 85% RH		
Ambient te	mperature	-40°C to 85°C		
Terminatio	n	QC		
Unit weight		Approx. 220g		
Construction	on	Dust protected		

Notes:	The	data	shown	above	are	initial	values.

COIL

Coil power	Single coil latching: Approx. 5W
	Double coils latching: Approx. 10W

at 23°C		COIL DATA				
Coil Resistance x (1±10%) Ω	Coil Resistance x (1±10%) Ω		Set / Reset Voltage VDC max.	Nominal Voltage VDC		
7.2		100	4.8	6		
le coil 28.8	Single coil	100	9.6	12		
ching 114	latching	100	19.2	24		
460		100	36.4	48		
3.6+3.6		100	4.8	6		
	Double coils	100	9.6	12		
57+57	latering	100	19.2	24		
230+230		100	36.4	48		

Nominal Voltage VAC	Set / Reset Voltage VAC max.	Pulse Duration ms min.	Coil Resistance x (1±10%) Ω	
230	161	50: full-wave rectification	Single coil latching	2420
230	161	100: half-wave rectification	Double coils latching	1210+1210

ELECTRICAL ENDURANCE

UC Class	Voltage (Uc)	Current (Ic)	Power Factor	Close Open time (s)		al endurance (OPS)
415 (UC1)	230VAC	80A	cosø=1	10:20	3000	Total:6000
		10A	COSØ=0.4		3000	
416 (UC2)		AC 80A	cosø=1		5000	Total:10000
			cosø=0.5		5000	
417 (UC3)		100A	COSØ=1		5000	Total:10000
			cosø=0.5		5000	

Remark:Electrical endurance meet IEC62055-31 test requirement, do the inductive load test after the resistive load test.

Only some typical ratings of UC are listed above, if more special ratings required, please contact us.



HONGFA RELAY

ISO9001, ISO/TS16949, ISO14001, OHSAS18001, IECQ QC 080000 CERTIFIED

27700VA/2800W

1 x 10⁵OPS

2015 Rev. 1.00

ORDERING INFORMATION /12 HFE28 -140 -2D Т 2 -R Type **140**: 140μΩ Sampling **280**: 280μΩ resistence Nil: Without sampling resistance Coil voltage 6, 12, 24, 48VDC; 230VAC 2D: 2 Form B (Single-contact) **2H:** 2 Form A (Single-contact) Contact form¹⁾⁾ **2SD:** 2 Form B (Double-contact of 2 Form B) 2SH: 2 Form A (Double-contact of 2 Form A) Contact material T: AgSnO2 Sort 1: Single coil latching 2: Double coils latching **Polarity** R: Negative polarity Nil: Positive polarity Special code^{2) 3)} XXX: Customer special requirement


Notes: 1) 2H, 2SH means that relay is on the "reset" status when delivery; 2D, 2SD means that relay is on the "set" status when delivery. If no speical required by customer, we will keep the relay on the "set" status when delivery.

- Please make clear your technical requirements, and choose from the following 3 UC ratings: UC1: meet the UC1 requirements on IEC62055-31: Carrying test 2400A peak current for 10ms; UC2: meet the UC2 requirements on IEC62055-31: Making test:2.5kA/10ms, carrying test 4.5kA/10ms;
 - UC3: meet the UC3 requirements on IEC62055-31: Making test:3kA/10ms, carrying test 6kA/10ms.
- 3) The customer special requirement express as special code after evaluating by Hongfa. e.g. (415) stands for UC1; e.g. (416) stands for UC2; e.g. (417) stands for UC3.

OUTLINE DIMENSIONS AND WIRING DIAGRAM


Unit: mm


Outline Dimensions




Remark: In case of no tolerance shown in outline dimension: outline dimension \leq 1mm, tolerance should be \pm 0.2mm; outline dimension >1mm and \leq 5mm, tolerance should be \pm 0.3mm; outline dimension >5mm, tolerance should be \pm 0.4mm.

Cage Clanp Terminal









Coil Wiring Diagram

Positive polarity



Negative polarity



Notice

- 1. Relay is on the "reset" or "set" status when being released from stock, with the consideration of shock risen from transit and relay mounting, relay would be changed to "set" or "reset" status, therefore, when application (connecting the power supply), please reset the relay to "set" or "reset" status on request.
- 2. In order to maintain "set" or "reset" status, energized voltage to coil should reach the rated voltage, impulse width should be 5 times more than "set" or "reset" time. Do not energize voltage to "set" coil and "reset" coil simultaneously. And also long energized time (more than 1 min) should be avoided.
- 3. The terminals of relay without twisted copper wire can not be tin-soldered, can not be moved willfully.
- 4. Relays used for metering measuring applications are usually made with dust proof structure, while most relays could be made specially per customer's specific requirements. No longer than 6 months' storage time is recommended for this kind of relay, and please pay attention to the storage environment. To ensure contact reliability, we will keep contact status be closed when delivery if no special required by customer.

Disclaimer

The specification is for reference only. See to "Terminology and Guidelines" for more information. Specifications subject to change without notice. We could not evaluate all the performance and all the parameters for every possible application. Thus the user should be in a right position to choose the suitable product for their own application. If there is any query, please contact Hongfa for the technical service. However, it is the user's responsibility to determine which product should be used only.

© Xiamen Hongfa Electroacoustic Co., Ltd. All rights of Hongfa are reserved.